arXiv:1209.4683v1 [cs.IT] 20 Sep 2012

Joint User Grouping and Linear Virtual Beamforming: Complexity, Algorithms and Approximation Bounds

Mingyi Hong, Zi Xu, Meisam Razaviyayn and Zhi-Quan Luo

Abstract

In a wireless system, by pooling distributed users to form a virtual multi-antenna system for joint transmission, the overall quality of the communication can be greatly improved. To reduce excessive overhead associated with large-scale user cooperation, the number of participating users must be well controlled. In this work, we consider the problem of properly selecting a subset of users (from potentially a large number of candidates) to form the virtual multi-antenna system, while at the same time designing their joint transmission strategies. In the aim of designing practical algorithms with provable theoretical performance, we focus on a class of simple yet important scenarios in which either multiple transmitters cooperatively transmit to a receiver, or a single transmitter transmits to the receiver with the help of a set of cooperative relays. We formulate the joint problems in different settings as cardinality constrained programs that contain both discrete and continuous variables. We then leverage the technique of semi-definite relaxation to obtain approximated solutions for them. The effectiveness of the proposed algorithms is evaluated via both theoretical analysis as well as extensive numerical experiments. We expect that our approach can be applied to solve cross-layer resource allocation problems in many other wireless communication systems as well.

Index Terms

Virtual Multi-antenna Systems, Beamforming, User Grouping, Cardinality Constrained Quadratic Program, Semi-definite Relaxation, Approximation Bounds

I. INTRODUCTION

With the proliferation of multimedia rich services as well as smart mobile devices, the demand for wireless data has been increasing explosively in recent years. To accommodate the growing demand for wireless data, the efficiency of spectrum utilization for future wireless systems needs to be significantly increased. Enabling cooperation among the nodes in a wireless system is regarded as an effective means for such purpose.

In a cellular network, cooperation can be achieved by allowing the neighboring base stations (BSs) to form a virtual multi-antenna system for cooperative transmission and reception. This scheme is referred to as the cooperative multipoint (ComP) scheme [1]. It can effectively cancel the inter-BS interference, and has been included into the next-generation wireless standards such as LTE-A (see e.g., [1]–[3]). For example, in a downlink network, assuming the users' data signals are known at all BSs, then either the capacity achieving non-linear dirty-paper coding

---

M. Hong, M. Razaviyayn and Z.-Q. Luo are with the Department of Electrical and Computer Engineering University of Minnesota, Minneapolis, USA. Z. Xu is with the Department of Mathematics, Shanghai University, Shanghai, China.

(DPC) (see, e.g., [4], [5]), or simpler linear precoding schemes such as zero-forcing (ZF) (see, e.g., [6]–[8]) can be used for joint transmission. On the other hand, various cooperation schemes that exploit the spatial diversity have been proposed to allow cooperation among the mobile users as well [9]–[15]. In these schemes, users assist each other in relaying information to the desired destinations, by employing different strategies such as amplify-and-forward (AF) and decode-and-forward (DF). When using the AF strategy, the system performance can be further improved if the relays jointly transmit using distributed space-time coding [9], [11], [16].

However, the cost of cooperation outweighs its benefit when the size of the cooperation group grows large. Such costs could be in the form of overhead incurred by exchanging control and data signals among the cooperative users (either via backhaul networks or air interfaces); it can also arise due to the difficulty in maintaining system level synchronization [2], [3], [17]. As a result, a pressing challenge in the design of cooperation protocols is to properly control the size of the cooperative groups while maintaining high system performance.

To address this issue, various *partial* cooperation scheme have been developed recently. In the setting of cellular network, partial cooperation among the BSs amounts to judiciously clustering the BSs into (possibly overlapping) small cooperation groups, within which they cooperatively transmit to the users. In references [7], [18], [19], cooperation clusters are formed either greedily or by an exhaustive search procedures. In [20], [21], a joint BS clustering and beamforming problem has been formulated as a *sparse* beamformer design problem, in which the sparsity of the virtual beamformer corresponds to the size of the cooperation groups. Partial cooperation in the relay networks has also been studied recently. In [14], [15], the authors proposed to select a *single* relay (out of many candidates) so that certain performance metric at the receiver is optimized. Alternatively, references [14], [22]–[24] study the *multiple* relay selection problem. In particular, the authors of [22] propose to increase the number of relays until adding an additional one decreases the received SNR. Reference [24] formulates the relay selection problem as a Knapsack problem [25], and proposes greedy algorithms for it. However, these schemes generally assume simplified underlying cooperation schemes after fixing the cooperative set. For example, references [7], [19] use simple zero forcing strategies for intra-cluster transmission; references [22], [23] assume that the cooperative relays transmit with full power. Moreover, there is little performance analysis for these partial cooperation schemes. This is due to the *mixed-integer* nature of the problem when including the group membership (which is a discrete variable) as optimization variables.

In this paper, we study the problem of optimally partitioning the users into cooperation groups, while at the same time designing their cooperation strategies. We focus on a class of simple yet important scenarios in which either multiple transmitters cooperatively transmit to a receiver, or a single transmitter transmits to the receiver with the help of a set of cooperative relays. The objective is to optimize the system performance measured by the receive signal to noise ratio (SNR), while explicitly constraining on the size of the cooperation group. We formulate the problems in different settings to cardinality constrained programs, and show that these problems are NP-hard in general. We further develop efficient algorithms using the technique called semi-definite relaxation (SDR) [26], [27], and analyze the quality of the proposed algorithms in terms of their gap to the global optimal solutions. The main novelty of this work lies in introducing the framework of SDR for the design of efficient partial cooperation schemes. Moreover, our work represents the first attempt to generalize the SDR approach (and its associated approximation bounds) to the mixed-integer cardinality constrained programs.

The rest of the paper is organized as follows. In Section II, we discuss the system model. Section III–Section V consider the joint user grouping and virtual beamforming problems in various settings. Section VI presents numerical results. The concluding remarks and future works are provided in Section VII.

Notations: For a symmetric matrix $\mathbf{X}$, $\mathbf{X} \succeq 0$ signifies that $\mathbf{X}$ is positive semi-definite. We use Tr$[\mathbf{X}]$, $\mathbf{X}^H$, and $\lambda_i(\mathbf{X})$ to denote the trace, hermitian, and the i-th largest eigenvalue of a matrix, respectively. Let $\mathrm{diag}(\mathbf{X})$ denote a matrix consisting the diagonal value of $\mathbf{X}$. Let $\mathcal{S}$ be an index set, we use $\mathbf{X}[i,j]$ and $\mathbf{X}[\mathcal{S}]$ to denote the (i,j)-th element of $\mathbf{X}$ and the principal submatrix of $\mathbf{X}$ indexed by the set $\mathcal{S}$, respectively. We use $\mathbf{x}[i]$ and $\mathbf{x}[\mathcal{S}]$ to denote the i-th element of the vector $\mathbf{x}$ and the subvector of $\mathbf{x}$ with the elements in set $\mathcal{S}$, respectively. For a complex scalar x, its complex conjugate is denoted by $\bar{x}$. Let $\delta_{i,j}$ denote the Kronecker function, which takes the value 1 if $i = j$, and 0 otherwise. $\mathbf{I}_n$ denotes an $n \times n$ identity matrix. We use $\mathbb{R}^{N\times M}$ and $\mathbb{C}^{N\times M}$ to denote the set of real and complex $N \times M$ matrices. We use $\mathbf{e}_i$ to denote the i-th unit vector and use $\mathbf{e}$ to denote the all 1 vector.

II. SYSTEM MODEL

Suppose there are a set $\mathcal{M} = \{1, \cdots, M\}$ of transmitters each equipped with a single antenna, and there is a single receiver with $N \geq 1$ receive antennas. Let $h_{i,n} \in \mathbb{C}$ denote the channel between transmitter i and the n-th antenna of the receiver, and let $\mathbf{h}_n \triangleq [h_{1,n}, \cdots, h_{M,n}]^H$. Suppose only second order statistics on the channels are available, that is, we only know $\mathbb{E}[\mathbf{h}_n \mathbf{h}_n^H] = \mathbf{R}_n \succ 0$, for $n = 1, \cdots, N$. Let $z \sim \mathcal{CN}(0,1)$ denote the (normalized) noise at the receiver. We restrict ourselves to the particular form of cooperation in which the cooperative nodes can form a *linear* virtual beamformer for joint transmission. Let $w_i \in \mathbb{C}$ denote the complex antenna gain for user i, which satisfies an individual transmit power constraint: $|w_i|^2 \leq P$. Define $\mathbf{w} \triangleq [w_1, \cdots, w_M]^H$.

When all the transmitters participate simultaneously in the beamforming, they transmit *the same* data signal to the receiver by using distinct antenna gains. When the system is viewed as a downlink network, such data sharing can be done via low-latency backhaul networks that connects the BSs. Alternatively, in the uplink, the users can share their data signals by the following steps: *1)* identify the user whose data is to be transmitted; *2)* the identified user broadcasts its data to all nearby users, who subsequently decode the data. For now we assume that when the system is viewed as an uplink network, the hop connecting the source and the cooperative users is *reliable*, in the sense that all the cooperative users can perfectly decode the signals in step 2). This assumption is reasonable as the cooperative users are usually located in close proximity (e.g., within the same office room). Consequently the bottleneck of the communication usually lies in the hop connecting the users to the BS. Later in Section V, we will consider the virtual beamforming problem in a relay network, which can incorporate the quality of the first hop communication into the formulation as well.

To simplify presentation, below we focus on an uplink case in which the users transmit to a BS. It should be understood, though, that our discussion is equally applicable to the downlink case (i.e., the ComP scheme) when the role of transmitters and receivers are reversed.

Assume that the BS performs spatially matched filtering/maximum ratio combining (which is equivalent to the MMSE receiver in this case), then the total received signal power can be expressed as: $\sum_{n=1}^{N}|\mathbf{h}_n^H\mathbf{w}|^2=\mathbf{w}^H\sum_{n=1}^{N}\mathbf{h}_n\mathbf{h}_n^H\mathbf{w}$. Let $\mathbf{R}\triangleq\sum_{n=1}^{N}\mathbb{E}[\mathbf{R}_n]$. The averaged signal to noise ratio (SNR) at the BS is then given by: $\mathrm{SNR}=\mathbb{E}\left[\sum_{n=1}^{N}|\mathbf{w}^H\mathbf{h}_n|^2\right]=\mathbf{w}^H\mathbf{R}\mathbf{w}$. To optimize the averaged SNR at the BS, one can solve the following quadratic program (QP)

$$\begin{aligned}\max_{\mathbf{w}}\quad & \mathbf{w}^H\mathbf{R}\mathbf{w} \\ \text{s.t.}\quad & |w_i|^2\le P,\ i=1,\cdots,M.\end{aligned}\tag{1}$$

As will be seen later in Section III-B, this seemingly simple problem turns out to be computationally very difficult for general channel covariance matrix $\mathbf{R}$.

It is worth mentioning that when the *instantaneous* channel states $\{\mathbf{h}_n\}$ are available, the sum SNR maximization problem is of the same form as in (1), with $\mathbf{R}$ replaced by $\widehat{\mathbf{R}}\triangleq\sum_{n=1}^{N}\mathbf{h}_n\mathbf{h}_n^H$. All our subsequent results carry over to this case as well. The reason that we interpret (1) as optimizing the averaged system performance is towfold: *1)* it may be difficult to obtain $\{\mathbf{h}_n\}$ exactly when the number of nodes is large; *2)* using instantaneous channel states for user grouping inevitably results in frequent change of group membership, which is usually costly.



Fig. 1. Illustration of joint user grouping and virtual beamforming. Users 1-3 and users 4, 5 are divided into two different groups.



Fig. 2. Illustration of joint relay selection and virtual beamforming. Relays 1-3 are chosen as the serving relays.

In practice, when the number of users becomes large, allowing all of them to cooperate at the same time induces heavy signaling overhead (related to users' exchange of data and control signals) and computational efforts (related to computing the optimal virtual beamformer for all the users) [17]. To address these issues, we propose to dividing the users into different cooperative groups while at the same time optimizing their virtual beamformers. We first consider a relatively simple case in which the aim is to find a *single* cooperative group with a fixed size. Such admission control problem is important as fixing the size of group can effectively control the cooperation and computational overhead. We then consider two more general cases in which either the users need to be allocated into groups that are served in orthogonal time slots, or there is an additional hop of transmission to be taken into consideration.

III. JOINT ADMISSION CONTROL AND VIRTUAL BEAMFORMING

A. System Model

Let Q denote the desired size of the cooperation group, and introduce the set of binary variables $a_i \in \{0,1\}, i \in \mathcal{M}$ to indicate the users' group membership: when $a_i = 1$, user i is being assigned to the cooperation group. Let $\mathbf{a} \triangleq [a_1, \cdots, a_M]$. Then the joint user grouping and beamforming problem is given as the following cardinality constrained program

$$\begin{aligned} v_1^{\mathrm{CP}} = \max_{\mathbf{w},\mathbf{a}} \quad & \mathbf{w}^H \mathbf{R} \mathbf{w} \\ \text{s.t.} \quad & |w_i|^2 \le a_i P,\ i = 1, \cdots, M \\ & \sum_{i=1}^{M} a_i = Q, \qquad a_i \in \{0,1\},\ i = 1, \cdots, M. \end{aligned} \tag{CP1}$$

Note that $a_i = 0$ implies $|w_i|^2 = 0$, that is, user i does not transmit. In the following, we will use $v_1^{\mathrm{CP}}(\mathbf{w})$ to indicate the objective value achieved by a feasible solution $\mathbf{w}$.

Introducing a homogenizing variable $\gamma \in \{-1, 1\}$ and change the domain of the discrete variables to $\{-1, 1\}$, the problem (CP1) can be equivalently reformulated as

$$\begin{aligned} \max_{\mathbf{w},\mathbf{a},\gamma} \quad & \mathbf{w}^H \mathbf{R} \mathbf{w} \\ \text{s.t.} \quad & \mathbf{w}^H \mathbf{e}_i \mathbf{e}_i^T \mathbf{w} + \frac{P}{4}(a_i - \gamma)^2 \le P,\ i = 1, \cdots, M \\ & \sum_{i=1}^{M} (a_i + \gamma)^2 = 4Q, \\ & a_i \in \{-1, 1\},\ i = 1, \cdots, M,\ \gamma \in \{-1, 1\}. \end{aligned}$$

After such transformation, we see that $\gamma \times a_i = 1$ implies $w_i \neq 0$, i.e., user i joins the cooperative group. To further simplify the problem, we introduce the following set of definitions

$$\mathbf{C}_{i,0} \triangleq \frac{1}{4}\mathbf{e}_i\mathbf{e}_i^T + \frac{1}{4}\mathbf{e}_{M+1}\mathbf{e}_{M+1}^T - \frac{1}{4}\mathbf{e}_i\mathbf{e}_{M+1}^T - \frac{1}{4}\mathbf{e}_{M+1}\mathbf{e}_i^T,\ \mathbf{C}_{i,1} \triangleq \mathbf{e}_i\mathbf{e}_i^T\frac{1}{P} \tag{2a}$$

$$\mathbf{D}_i \triangleq \text{blkdg}[\mathbf{C}_{i,0}, \mathbf{C}_{i,1}] \in \mathbb{C}^{(2M+1)\times(2M+1)} \tag{2b}$$

$$\widetilde{\mathbf{R}} \triangleq \text{blkdg}[\mathbf{0}, \mathbf{R}] \in \mathbb{C}^{(2M+1)\times(2M+1)} \tag{2c}$$

$$\mathbf{B}_0 \triangleq \begin{bmatrix} \mathbf{I} & \mathbf{e} \\ \mathbf{e}^T & M \end{bmatrix} \in \mathbb{R}^{(M+1)\times(M+1)},\ \mathbf{B} = \text{blkdg}[\mathbf{B}_0, \mathbf{0}] \in \mathbb{R}^{(2M+1)\times(2M+1)} \tag{2d}$$

$$\mathbf{x} \triangleq [\mathbf{a}^T, \gamma, \mathbf{w}^T]^T\ \mathbf{x}_0 \triangleq [\mathbf{a}^T, \gamma]^T, \mathbf{x}_1 \triangleq \mathbf{w}. \tag{2e}$$

Then the problem (CP1) can be further simplified as

$$\max_{\mathbf{x}} \quad \mathbf{x}^H\widetilde{\mathbf{R}}\mathbf{x} \tag{R1}$$

$$\text{s.t.} \quad \mathbf{x}^H\mathbf{D}_i\mathbf{x} \le 1,\ i = 1\cdots, M \tag{3a}$$

$$\mathbf{x}^H\mathbf{B}\mathbf{x} = 4Q, \tag{3b}$$

$$\mathbf{x}[i] \in \{-1, 1\},\ i = 1, \cdots, M+1.$$

We emphasize again that in this new notation, $\mathbf{x}[i]\mathbf{x}[M+1] = 1$ implies $\mathbf{x}[M+1+i] \neq 0$.

B. The Complexity of the Problem (CP1)

In fact, solving problem (CP1) (or equivalently problem (R1)) is challenging. In this subsection, we show that this problem is strongly NP-hard. To this end, it is sufficient to show that even when fixing the values of the binary variables $\{a_i\}$, the problem is still NP-hard.

Let $\mathcal{S} \subset \mathcal{M}$ with $|\mathcal{S}| = Q$ denote the *support* of a feasible solution $\mathbf{w}$ to problem (CP1): $\mathcal{S} = \{i : a_i = 1\}$. When $\mathcal{S}$ is fixed, problem (CP1) is equivalent to the following QP

$$\max_{\widetilde{\mathbf{w}} \in \mathbb{C}^Q} \quad \widetilde{\mathbf{w}}^H\mathbf{R}[\mathcal{S}]\widetilde{\mathbf{w}} \tag{QP1}$$

$$\text{s.t.} \quad |\widetilde{w}_i|^2 \le P, i = 1, \cdots, Q.$$

In the following we analyzes the computational complexity for (QP1).

Proposition 1 *Solving the problem* (QP1) *is NP-hard in the number of users.*

Proof: We only prove the claim with real variables. The complex case can be derived similarly. The claim is proved by a polynomial time reduction from a known NP-complete problem called equal partition problem [25], which can be described as follows. Given a vector $\mathbf{c}$ consisting of positive integers $c_1, \cdots, c_Q$, decide whether there exists a subset $\mathcal{I}$ such that

$$\frac{1}{2}\sum_{i=1}^{Q} c_i = \sum_{i\in\mathcal{I}} c_i. \tag{4}$$

Suppose $\mathbf{c}^T\mathbf{c} = C$. Let $\mathbf{R}[\mathcal{S}] = (-\mathbf{c}\mathbf{c}^T + 2C\mathbf{I}_Q) \succ 0$. The claim is that the problem (QP1) has the maximum value of $2CQP$ if and only if there exists a set $\mathcal{I}$ satisfying (4). With this specific structure of $\mathbf{R}[\mathcal{S}]$, the objective of problem (QP1) can be written as

$$\widetilde{\mathbf{w}}^T\mathbf{R}[\mathcal{S}]\widetilde{\mathbf{w}} = -|\widetilde{\mathbf{w}}^T\mathbf{c}|^2 + 2C\sum_{i=1}^{Q}|\widetilde{w}_i|^2 \le 2C\sum_{i=1}^{Q}|\widetilde{w}_i|^2 \le 2CQP, \text{ whenever } |\widetilde{w}_i|^2 \le P. \tag{5}$$

Consequently, the maximum value for problem (QP1) is $2CQP$ iff $-|\widetilde{\mathbf{w}}^T\mathbf{c}|^2 = 0$ and $|\widetilde{w}_i|^2 = P$. This is equivalent to the existence of an index set $\mathcal{I}$ such that (4) is true. ■

We note that the difficulty in solving problem (QP1) can be mainly attributed to the set of individual power constraints. If we only have a *total power constraint* in the form of $\|\widetilde{\mathbf{w}}\| \le P$, then this problem is simply the principal component analysis (PCA) problem. In this case, the original problem (CP1) becomes one that finds a $Q \times Q$ principal submatrix of $\mathbf{R}$ that yields the maximum eigenvalue (or equivalently, the *sparse* PCA problem, see [28]). This problem is still difficult to solve, but there are efficient heuristic algorithms for it, see [28], [29].

Remark 1 The result obtained in Proposition 1 asserts that (QP1) is difficult to solve for *general* $\mathbf{R}$. However when $\mathbf{R}$ admits certain special structures, both (QP1) and (CP1) may be easy to solve. One such example is that when $\mathbf{R}$ is a rank 1 matrix, i.e., $\mathbf{R} = \mathbf{r}\mathbf{r}^H$ for some vector $\mathbf{r} \in \mathbb{C}^M$. This channel model may be of interests as it corresponds to the special case in which the receiver has a single antenna, and the *instantaneous* SNR is considered. Another relevant special case is that when $\mathbf{R}$ is a diagonal matrix, which happens when all the users' channels are *independent*. For both cases, problems (QP1) and (CP1) are separable among the variables, and their solutions can be easily obtained in closed form.

C. The Semi-definite Relaxation

Our proposed algorithm is based on the technique called semi-definite relaxation (SDR), which has been widely used to solve problems in communications and signal processing [26]. We emphasize that unlike conventional SDR methods (such as those surveyed in [26]), in which the problems to be relaxed have either all continuous (e.g., [27]) or all discrete (e.g., [30]) variables, our problem (CP1) (or equivalently (R1)) is of *mixed integer* nature. Consequently our algorithm and analysis differ significantly from those developed in the literature.

We first introduce two semi-definite programs. Define a variable $\mathbf{X} \triangleq \mathbf{x}\mathbf{x}^H$. Define two index sets $\mathcal{I} \triangleq \{1, \cdots, M+1\}$ and $\bar{\mathcal{I}} \triangleq \{M+2, \cdots, 2M+1\}$. Then $\mathbf{X}_0 \triangleq \mathbf{X}[\mathcal{I}]$ and $\mathbf{X}_1 \triangleq \mathbf{X}[\bar{\mathcal{I}}]$ denote the leading and trailing principal submatrices of $\mathbf{X}$, respectively. Clearly $\mathbf{X}_0 = \mathbf{x}_0\mathbf{x}_0^T$ and $\mathbf{X}_1 = \mathbf{x}_1\mathbf{x}_1^H$. Moreover, we have $\text{Rank}(\mathbf{X}) = 1$ and $\mathbf{X}_0[i,j] \in \{-1, 1\}$ for all $i, j \in \mathcal{I}$. The following semi-definite program is a relaxation of (R1), by removing the non-convex constraint $\text{Rank}(\mathbf{X}) = 1$ and by replacing $\mathbf{X}_0[i,j] \in \{-1,1\}$ by $\mathbf{X}_0[i,j] \in [-1,1]$, for all $i, j \in \mathcal{I}$:

$$v_1^{\text{SDP}} = \max_{\mathbf{X}\succeq 0} \quad \text{Tr}[\widetilde{\mathbf{R}}\mathbf{X}] \tag{SDP1}$$

$$\text{s.t.} \quad \text{Tr}[\mathbf{D}_i\mathbf{X}] \le 1, \; i = 1\cdots, M \tag{6a}$$

$$\text{Tr}[\mathbf{B}\mathbf{X}] = 4Q \tag{6b}$$

$$\mathbf{X}[i,i] = 1, i = 1, \cdots, M+1. \tag{6c}$$

Note that we did not explicitly include the conditions $\mathbf{X}_0[i,j]\in[-1,1]$, for all $i,j\in\mathcal{I}$, as it can be ensured by the set of conditions (6c) and $\mathbf{X}\succeq 0$. As the above problem is a relaxation of problem (R1), we must have $v_1^{\rm SDP}\ge v_1^{\rm QP}$. Denote the optimal solution for this problem as $\mathbf{X}^*$. Without loss of generality we can assume $\mathbf{X}^*=\mathrm{blkdg}[\mathbf{X}_0^*,\mathbf{X}_1^*]$.

Similarly, let $\mathbf{Y}\triangleq\widetilde{\mathbf{w}}\widetilde{\mathbf{w}}^H\in\mathbb{C}^{Q\times Q}$. The following problem is a relaxation of the problem (QP1), for a given index set $\mathcal{S}\subseteq\mathcal{M}$ with $|\mathcal{S}|=Q$

$$\max_{\mathbf{Y}\succeq 0}\quad \mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}] \tag{7a}$$

$$\text{s.t.}\quad \mathbf{Y}[i,i]\le P, i=1,\cdots,Q. \tag{7b}$$

Let us denote the optimal solution of this problem by $\mathbf{Y}^*$.

The following remarks summarize some useful properties of the these two problems.

Remark 2 At optimality, the set of constraints (6a) and (7b) must be all tight.

We show the tightness for (6a). The case for (7b) can be argued similarly. Suppose on the contrary, there exists $i\in\mathcal{M}$ such that $\mathrm{Tr}[\mathbf{D}_i\mathbf{X}^*]<1$. Then from the definition of $\mathbf{D}_i$ in (2b), we have: $\mathrm{Tr}[\mathbf{C}_{i,1}\mathbf{X}_1^*]+\mathrm{Tr}[\mathbf{C}_{i,0}\mathbf{X}_0^*]<1$, which is equivalent to: $\frac{1}{P}\mathbf{X}_1^*[i,i]<\frac{1}{2}+\frac{1}{2}\mathbf{X}_0^*[i,M+1]$. Due to the assumption that the inequality is strict, we can find a constant $\delta>0$ such that

$$\frac{1}{P}\mathbf{X}_1^*[i,i]+\delta=\frac{1}{2}+\frac{1}{2}\mathbf{X}_0^*[i,M+1].$$

As a result, let $\widehat{\mathbf{X}}_1=\mathbf{X}_1^*+\delta\mathbf{e}_i\mathbf{e}_i^T\succeq 0$, then $\widehat{\mathbf{X}}=\mathrm{blkdg}[\mathbf{X}_0^*,\widehat{\mathbf{X}}_1]$ is also feasible for (SDP1). This alternative solution achieves the following objective

$$v_1^{\rm SDP}(\widehat{\mathbf{X}})=\mathrm{Tr}[\mathbf{R}(\mathbf{X}_1^*+\delta\mathbf{e}_i\mathbf{e}_i^T)]=\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*]+\delta\mathrm{Tr}[\mathbf{R}\mathbf{e}_i\mathbf{e}_i^T]\overset{(a)}{>}\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*], \tag{8}$$

where in (a) we have used that fact that $\delta>0$ and $\mathbf{R}[i,i]>0$ (due to the strict positive definiteness of $\mathbf{R}$). Clearly, the inequality (8) is a contradiction to the optimality of $\mathbf{X}^*$.

In conclusion, we have

$$\frac{1}{P}\mathbf{X}_1^*[i,i]=\frac{1}{2}+\frac{1}{2}\mathbf{X}_0^*[i,M+1],\ \forall\ i=1,\cdots,M. \tag{9}$$

Remark 3 The sum of the last column of $\mathbf{X}_0^*$ admits a closed form expression. Note that the cardinality constraint (6b) implies that $2\sum_{i=1}^M\mathbf{X}_0^*[i,M+1]+2M=4Q$, which is further equivalent to: $\sum_{i=1}^M\mathbf{X}_0^*[i,M+1]=2Q-M$.

D. The Proposed Algorithm

In this section, we propose a randomized algorithm that generates an approximated solution to the problem (CP1). To highlight, we first list the main steps of the algorithm:

1) Compute the optimal solution $\mathbf{X}^*$ of the relaxation problem (SDP1);
2) Determine the discrete variables x_0 and the set $\mathcal{S}$ according to $\mathbf{X}_0^*$;

3) Fixing $\mathcal{S}$, compute the optimal solution $\mathbf{Y}^*$ of problem (7a);
4) Randomly generating a sample of feasible $\mathbf{w}$'s using $\mathbf{Y}^*$;
5) Select the solution that achieves the best objective value for problem (CP1).

The distinctive feature of the proposed algorithm, compared to many SDR-based algorithm, is mainly in steps 2)–4), in which the solution $\mathbf{X}^*$ is converted to a vector $\mathbf{w}$ with prescribed number of zero components. It is worth noting that the proposed algorithm generates an approximated solution with guaranteed quality (see Section III-E for detail).

To formally describe the proposed algorithm, the following definitions are needed. Let $\mathcal{S} \subseteq \mathcal{M}$ be an index set. Decompose $\mathbf{Y}^*$ by $\mathbf{Y}^* = \mathbf{\Delta}^H \mathbf{\Delta}$. Then define

$$\mathbf{\Omega}(\mathcal{S}) \triangleq \sum_{i \in \mathcal{S}} \mathbf{e}_i \mathbf{e}_i^T \in \mathbb{R}^{M \times M}$$

$$\mathbf{E}_i \triangleq \mathbf{\Delta} \mathbf{C}_{i,1}[\mathcal{S}] \mathbf{\Delta}^H, \ \mathbf{E} \triangleq \mathbf{\Delta} \mathbf{R}[\mathcal{S}] \mathbf{\Delta}^H.$$

Note that for an arbitrary $M \times M$ matrix, multiplying $\mathbf{\Omega}(\mathcal{S})$ from both right and left leads to a matrix that has nonzero elements only in rows and columns indexed by $\mathcal{S}$. Let us further decompose $\mathbf{E}$ by: $\mathbf{E} = \mathbf{U} \mathbf{\Sigma} \mathbf{U}^H$. Then the diagonal matrix $\mathbf{\Sigma}$ can be expressed as

$$\mathbf{\Sigma} = \mathbf{U}^H \mathbf{E} \mathbf{U} = \mathbf{U}^H \mathbf{\Delta} \mathbf{R}[\mathcal{S}] \mathbf{\Delta}^H \mathbf{U}. \tag{10}$$

Define $\widehat{\mathbf{E}}_i \triangleq \mathbf{U}^H \mathbf{E}_i \mathbf{U}$.

Let us use L to denote the sample size of the randomization procedure, and use (l) to denote the index of a random sample. Let $\underline{\mathbf{x}}_{(Q)}$ and $\underline{\mathbf{r}}_{(Q)}$ respectively denote the Q-th largest value in the sets $\{\mathbf{X}_0^*[i, M+1]\}_{i=1}^M$ and $\{\mathbf{R}[i,i]\}_{i=1}^M$. The proposed algorithm is listed in Table I.

TABLE I
THE PROPOSED ALGORITHM FOR ADMISSION CONTROL

```
S1: Compute the solution $\mathbf{X}^*$ of problem (SDP1)
S2: Find a set $\mathcal{T}$ of indices such that $|\mathcal{T}| = Q$ and
        $\mathcal{T} = \{j : \mathbf{X}_0^*[j, M+1] \geq \underline{\mathbf{x}}_{(Q)}\}$;
    S2a: If    $\mathrm{Tr}[\mathbf{R}\mathbf{\Omega}(\mathcal{T})\mathbf{X}_1^*\mathbf{\Omega}(\mathcal{T})] \geq \frac{QP}{M}\mathrm{Tr}[\mathbf{R}]$, let $\mathcal{S} = \mathcal{T}$;
    S2b: Else  Let $\mathcal{S} = \{j : \mathbf{R}[i,i] \geq \underline{\mathbf{r}}_{(Q)}\}$;
    Let $\bar{\mathcal{S}} = \mathcal{M} \setminus \mathcal{S}$;
S3: Set $\mathbf{x}_0[M+1] = 1$ and $\mathbf{x}_0[j] = 1$, for all $j \in \mathcal{S}$;
    Set $\mathbf{x}_0[i] = -1$ for all $i \in \bar{\mathcal{S}}$;
S4: Compute the solution $\mathbf{Y}^*$ of problem (7a) with index set $\mathcal{S}$;
For $\ell = 1, \cdots, L$
S5: Generate $\boldsymbol{\xi}^{(\ell)} \in \{-1,1\}^Q$ by randomly and independently
    generating its components uniformly from $\{-1,1\}$;
S6: Compute $t^{(\ell)} = \sqrt{\max_{i \in \mathcal{S}} (\boldsymbol{\xi}^{(\ell)})^T \widehat{\mathbf{E}}_i \boldsymbol{\xi}^{(\ell)}}$;
S7: Compute $\widetilde{\mathbf{w}}^{(\ell)} = \frac{1}{t^{(\ell)}} \mathbf{\Delta}^H \mathbf{U} \boldsymbol{\xi}^{(\ell)}$;
    Let $\mathbf{w}^{(\ell)}[\mathcal{S}] = \widetilde{\mathbf{w}}^{(\ell)}$ and $\mathbf{w}^{(\ell)}[\bar{\mathcal{S}}] = \mathbf{0}$;
End For
S8: Compute $\ell^* = \arg_\ell \max (\mathbf{w}^{(\ell)})^H \mathbf{R} \mathbf{w}^{(\ell)}$; let $\mathbf{w}^* = \mathbf{w}^{(\ell^*)}$;
```

This algorithm can be viewed as a generalization of the algorithm developed by Nemirovski et al. and Zhang et al. [31], [32] for approximating continuous quadratic programs. The novelty of this algorithm mainly lies in Step S2)–Step S3), in which discrete variables are determined. Below we motivate Step S2). Note that without rank relaxation, $\mathbf{X}_0 = \mathbf{x}_0\mathbf{x}_0^T$ is the block variable representing the discrete variables, so it is reasonable to select cooperative groups using the elements of this matrix. Furthermore, recall that in problem (R1), a user i joins the cooperative group if $\mathbf{x}_0[i]\mathbf{x}_0[M+1] = 1$, which, combined with the definition $\mathbf{X}_0 = \mathbf{x}_0\mathbf{x}_0^T$, implies that $\mathbf{X}_0[i, M+1] = 1$. Ideally, we should form the cooperative group by choosing Q elements in the set $\widetilde{\mathcal{S}} = \{i : \mathbf{X}_0^*[i, M+1] = 1, i \in \mathcal{M}\}$. However it is possible that $|\widetilde{\mathcal{S}}| < Q$, as we have relaxed the non-convex condition $\mathbf{X}_0[i,j] \in \{-1, 1\}$ to $\mathbf{X}_0[i,j] \in [-1, 1]$. As a result, we instead choose the largest Q elements in the set $\{\mathbf{X}^*[i, M+1]\}_{i=1}^M$. Step 2a)-2b) are some technical refinement of the selection procedure that are needed later for the proof of the approximation bounds. We note here that in our numerical experiments, we find that the cooperative set is almost always determined by the set $\mathcal{T}$, and Step 2b) rarely gets executed. The reason for using Step S4)-S8) to generate a feasible solution $\mathbf{w}^*$ can be explained by the following two remarks.

Remark 4 The objective value of the problem (CP1) evaluated at a solution $\mathbf{w}^{(\ell)}$ is given by

$$\begin{aligned} v_1^{\mathrm{CP}}(\mathbf{w}^{(\ell)}) &= (\mathbf{w}^{(\ell)})^H \mathbf{R}\mathbf{w}^{(\ell)} = \frac{1}{(t^{(\ell)})^2}(\boldsymbol{\xi}^{(\ell)})^T \mathbf{U}^H \boldsymbol{\Delta}\mathbf{R}[\mathcal{S}]\boldsymbol{\Delta}^H \mathbf{U}\boldsymbol{\xi}^{(\ell)} \\ &\overset{(a)}{=} \frac{1}{(t^{(\ell)})^2}(\boldsymbol{\xi}^{(\ell)})^T \boldsymbol{\Sigma}\boldsymbol{\xi}^{(\ell)} \overset{(b)}{=} \frac{1}{(t^{(\ell)})^2}\mathrm{Tr}[\boldsymbol{\Sigma}] \overset{(c)}{=} \frac{1}{(t^{(\ell)})^2}\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \end{aligned} \tag{11}$$

where (a) is from (26); (b) is from the fact that $\boldsymbol{\Sigma}$ is diagonal, and the diagonal elements of $\boldsymbol{\xi}^{(\ell)}(\boldsymbol{\xi}^{(\ell)})^T$ are all 1; (c) is from the definition of $\boldsymbol{\Sigma}$.

Remark 5 We claim that for all $l = 1, \cdots, L$, the solution $\mathbf{x}^{(\ell)} \triangleq [\mathbf{x}_0^H, (\mathbf{w}^{(\ell)})^H]^H$ is a feasible solution for the problem (R1). Moreover, $\mathbf{w}^{(\ell)}$ is a feasible solution to (CP1).

First we show that the constraint $(\mathbf{x}^{(\ell)})^H \mathbf{D}_i \mathbf{x}^{(\ell)} \leq 1$ is always satisfied for all $i \in \mathcal{M}$. To see this, we consider the following two cases (we omit the superscript (ℓ) for notational simplicity).

Case i): If $i \in \mathcal{S}$, then we have

$$\begin{aligned} \mathbf{x}^H \mathbf{D}_i \mathbf{x} &= (\mathbf{w})^H \mathbf{C}_{i,1}\mathbf{w} + (\mathbf{x}_0)^H \mathbf{C}_{i,0}\mathbf{x}_0 \\ &= (\boldsymbol{\Omega}(\mathcal{S})\mathbf{w})^H \mathbf{C}_{i,1}\boldsymbol{\Omega}(\mathcal{S})\mathbf{w} + (\mathbf{x}_0)^H \mathbf{C}_{i,0}\mathbf{x}_0 \\ &= (\mathbf{w}[\mathcal{S}])^H \mathbf{C}_{i,1}[\mathcal{S}]\mathbf{w}[\mathcal{S}] + (\mathbf{x}_0)^H \mathbf{C}_{i,0}\mathbf{x}_0 \\ &= \frac{1}{t^2}\boldsymbol{\xi}^T \mathbf{U}^H \boldsymbol{\Delta}\mathbf{C}_{i,1}[\mathcal{S}]\boldsymbol{\Delta}^H \mathbf{U}\boldsymbol{\xi} + \frac{1}{2}(1 - \mathbf{x}_0[i]\mathbf{x}_0[M+1]) \\ &\overset{(a)}{=} \frac{1}{t^2}\boldsymbol{\xi}^T \widehat{\mathbf{E}}_i \boldsymbol{\xi} \overset{(b)}{\leq} 1 \end{aligned}$$

where (a) is from the definition of $\widehat{\mathbf{E}}_i$ and from the fact that $\mathbf{x}_0[M+1] = 1$ and for all $i \in \mathcal{S}$, $\mathbf{x}_0[i] = 1$; (b) is from the definition of t in Step S6) of the algorithm.

Case ii): If $i \in \bar{\mathcal{S}}$, then from Step S7) of the algorithm, we have $w_i = 0$. Using the fact that $\mathbf{C}_{i,1} = \mathbf{e}_i \mathbf{e}_i^T \frac{1}{P}$, we have: $\mathbf{x}^H \mathbf{D}_i \mathbf{x} = (\mathbf{w})^H \mathbf{C}_{i,1} \mathbf{w} = |w_i|^2 \frac{1}{P} = 0$. It is straightforward to see that the cardinality constraint $\mathbf{x}^H \mathbf{B} \mathbf{x} = 4Q$ is satisfied for each solution $\mathbf{w}^{(\ell)}$, as this constraint mandates that $M - Q$ users do not transmit.

In summary, we conclude that $\mathbf{x}$ is feasible for the problem (R1). Due to the equivalence between problems (R1) and (CP1), $\mathbf{w}$ is also feasible for the latter problem.

E. The Analysis of the Quality of the Solution

We are now ready to analyze the quality of the solution generated by our proposed algorithm. Naturally, such quality should be measured by comparing the achieved objective to the globally optimal objective $v_1^{\rm CP}$. More specifically, we would like to find a constant $\alpha_1 > 1$ such that: $v_1^{\rm CP}(\mathbf{w}^*) \ge \frac{1}{\alpha_1} v_1^{\rm CP}$. The constant α_1 is referred to as the *approximation ratio* of the solution $\mathbf{w}^*$. The smaller the value of α_1, the better the quality of the solution $\mathbf{w}^*$. However, due to the NP-hardness of solving problem (R1), $v_1^{\rm CP}$ is generally difficult to compute. Alternatively, in the following we will find a constant α_1 that satisfies$v_1^{\rm CP}(\mathbf{w}^*) \ge \frac{1}{\alpha_1} v_1^{\rm SDP}$. Note that the latter inequality implies the former, as $v_1^{\rm SDP} \ge v_1^{\rm CP}$. We have the following results regarding to the quality of solution $\mathbf{w}^*$.

Theorem 1 *If $\mathbf{w}^*$ is generated using the algorithm in Table I, then with high probability, we have $v_1^{\rm CP}(\mathbf{w}^*) \ge \frac{1}{\alpha_1} v_1^{\rm SDP}$, with α_1 bounded by*

$$\alpha_1 \le \frac{8M\lambda_1(\mathbf{R})}{\sum_{i=1}^M \lambda_i(\mathbf{R})} \ln(5Q) < 8M \ln(5Q). \tag{12}$$

Proof: To show Theorem 1, below we first show that for any $\ell = 1, \cdots, L$, there exists a constant α_1 satisfying $1 < \alpha_1 < \infty$ such that: ${\rm Prob}\left(v_1^{\rm CP}(\mathbf{w}^{(\ell)}) \ge \frac{1}{\alpha_1} v_1^{\rm SDP} \right) \ge \delta > 0$, or equivalently,

$${\rm Prob}\left(\frac{1}{(t^{(\ell)})^2} {\rm Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \ge \frac{1}{\alpha_1} {\rm Tr}[\mathbf{R}\mathbf{X}_1^*] \right) \ge \delta > 0. \tag{13}$$

That is, with positive probability, the solution $\mathbf{w}^{(\ell)}$ generated by the proposed algorithm is at least as good as $\frac{1}{\alpha_1}$ fraction of $v^{\rm SDP}$. It follows that the probability that the solution $\mathbf{w}^*$ achieves an objective that is at least $\frac{1}{\alpha_1}$ of $v_1^{\rm SDP}$ is given by

$$\begin{aligned}
&{\rm Prob}\left(\max_{\ell} v_1^{\rm CP}(\mathbf{w}^{(\ell)}) \ge \frac{1}{\alpha_1} v_1^{\rm CP} \right) \\
&\ge {\rm Prob}\left(\max_{\ell} v_1^{\rm CP}(\mathbf{w}^{(\ell)}) \ge \frac{1}{\alpha_1} v_1^{\rm SDP} \right) = 1 - {\rm Prob}\left(\max_{\ell} v_1^{\rm CP}(\mathbf{w}^{(\ell)}) < \frac{1}{\alpha_1} v_1^{\rm SDP} \right) \\
&= 1 - \prod_{l=1}^{L} {\rm Prob}\left(v_1^{\rm CP}(\mathbf{w}^{(\ell)}) < \frac{1}{\alpha_1} v_1^{\rm SDP} \right) \ge 1 - (1-\delta)^L.
\end{aligned}$$

Clearly, this probability approaches 1 exponentially as L becomes large.

Below we will show (13). The analysis is divided into the following three steps.

Step 1): Let $\beta > 0$ be a constant. We first show that when $\frac{\beta}{\alpha_1}$ is small enough, with zero probability the event $\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \le \frac{\beta}{\alpha_1}\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*]$ happens.

To this end, we first lower bound $\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*]$. We have the following two cases.

Case i) Suppose $\mathcal{S} = \mathcal{T} = \{j : \mathbf{X}_1^*[j, M+1] \ge \underline{\mathbf{x}}\}$, then we have

$$v_2^{\mathrm{SDP}} = \mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \overset{\text{(i)}}{\ge} \mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{X}_1^*[\mathcal{S}]] = \mathrm{Tr}[\boldsymbol{\Omega}(\mathcal{S})\mathbf{R}\boldsymbol{\Omega}(\mathcal{S})\boldsymbol{\Omega}(\mathcal{S})\mathbf{X}_1^*\boldsymbol{\Omega}(\mathcal{S})] \overset{\text{(ii)}}{=} \mathrm{Tr}[\mathbf{R}\boldsymbol{\Omega}(\mathcal{S})\mathbf{X}_1^*\boldsymbol{\Omega}(\mathcal{S})]$$

where (i) is from that fact $\mathbf{X}_1^*[\mathcal{S}]$ is a feasible solution to the problem (7a), and that $\mathbf{Y}^*$ is the optimal solution for that problem; (ii) is because $\boldsymbol{\Omega}(\mathcal{S})\boldsymbol{\Omega}(\mathcal{S}) = \boldsymbol{\Omega}(\mathcal{S})$. From Step S2) of the algorithm, we must have $\mathrm{Tr}[\mathbf{R}\boldsymbol{\Omega}(\mathcal{S})\mathbf{X}_1^*\boldsymbol{\Omega}(\mathcal{S})] \ge \frac{QP}{M}\mathrm{Tr}[\mathbf{R}]$, it follows that

$$\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \ge \frac{QP}{M}\mathrm{Tr}[\mathbf{R}]. \tag{14}$$

Case ii) Suppose $\mathcal{S} = \{j : \mathbf{R}[i,i] \ge \underline{\mathbf{r}}\}$. Then we have

$$\mathrm{Tr}\left[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*\right] \overset{\text{(i)}}{\ge} P \times \mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{I}_Q] \overset{\text{(ii)}}{\ge} \frac{QP}{M}\mathrm{Tr}[\mathbf{R}] \tag{15}$$

where (i) is again from that fact $P\mathbf{I}_Q$ is a feasible solution to the problem (7a), and that $\mathbf{Y}^*$ is the optimal solution for that problem; (ii) is from the fact that each $i \in \mathcal{S}$ is among the largest Q elements in the set $\{\mathbf{R}[i,i]\}_{i=1}^{Q}$, which leads to $\sum_{i\in\mathcal{S}}\mathbf{R}[i,i] \ge \frac{Q}{M}\sum_{i=1}^{M}\mathbf{R}[i,i] = \frac{Q}{M}\mathrm{Tr}[\mathbf{R}]$.

We then upper bound $\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*]$. By a trace inequality for the product of two semi-definite matrices, we have that [33]

$$\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*] \le \sum_{i=1}^{M}\lambda_i\left(\mathbf{X}_1^*\right)\lambda_i(\mathbf{R}) \le \lambda_1(\mathbf{R})\sum_{i=1}^{M}\lambda_i\left(\mathbf{X}_1^*\right) = \lambda_1(\mathbf{R})\mathrm{Tr}[\mathbf{X}_1^*]. \tag{16}$$

Utilizing this result, we have

$$\begin{aligned}
\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*] \le \lambda_1(\mathbf{R})\mathrm{Tr}[\mathbf{X}_1^*] &\overset{\text{(i)}}{=} P\lambda_1(\mathbf{R})\sum_{i=1}^{M}\left(\frac{1}{2} + \frac{1}{2}\mathbf{X}_0^*[i, M+1]\right)\\
&= P\lambda_1(\mathbf{R})\left(\frac{M}{2} + \frac{1}{2}\sum_{i=1}^{M}\mathbf{X}_0^*[i, M+1]\right)\\
&\overset{\text{(ii)}}{=} P\lambda_1(\mathbf{R})\left(\frac{2Q-M}{2} + \frac{M}{2}\right) = QP\lambda_1(\mathbf{R})
\end{aligned} \tag{17}$$

where (i) is from the tightness of the first set of constraints of the problem (SDP1) (cf. (9)) and (ii) is due to Remark 2 and Remark 3. Comparing (15) and (17), we see that choosing $\frac{\beta}{\alpha_1} \le \frac{\mathrm{Tr}[\mathbf{R}]}{M\lambda_1(\mathbf{R})}$ ensures

$$\mathrm{Prob}\left(\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \le \frac{\beta}{\alpha_1}\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*]\right) = 0.$$

Step 2): For fixed α_1, we bound the probability that $\mathrm{Prob}\left(\frac{1}{(t^{(\ell)})^2} \le \frac{1}{\beta}\right)$ as follows (omitting (ℓ) for simplicity)

$$\mathrm{Prob}\left(\frac{1}{t^2} \le \frac{1}{\beta}\right) = \mathrm{Prob}(t^2 \ge \beta) = \mathrm{Prob}\left(\max_{i\in\mathcal{S}} (\boldsymbol{\xi})^T \widehat{\mathbf{E}}_i \boldsymbol{\xi} \ge \beta\right)$$
$$\le \sum_{i\in\mathcal{S}} \mathrm{Prob}\left((\boldsymbol{\xi})^T \widehat{\mathbf{E}}_i \boldsymbol{\xi} \ge \beta\right) < 4Q\mu \exp\left(-\frac{\beta}{8}\right)$$

where $\mu = \min[Q, \max_i \mathrm{Rank}(\widehat{\mathbf{E}}_i)]$. The last inequality is obtained by slightly generalizing the existing result in [31, Proposition 1] [1]. To explicitly compute the value for μ, note that by definition, we have

$$\widehat{\mathbf{E}}_i = \mathbf{U}^H \mathbf{E}_i \mathbf{U} = \mathbf{U}^H \boldsymbol{\Delta} \mathbf{C}_{i,1}[\mathcal{S}] \boldsymbol{\Delta}^H \mathbf{U}.$$

As a result, $\mathrm{Rank}(\widehat{\mathbf{E}}_i) \le 1$ as by definition $\mathrm{Rank}(\mathbf{C}_{i,1}) = 1$, and any one of its principal submatrix must have rank at most 1. We conclude that $0 \le \mu \le 1$.

Step 3): Utilizing the above result, choose

$$\beta = 8\ln(5Q),\ \alpha_1 = \frac{8M\lambda_1(\mathbf{R})}{\mathrm{Tr}[\mathbf{R}]}\ln(5Q),$$

we can bound the left hand side of (13) as follows

$$\begin{aligned}
&\mathrm{Prob}\left(\frac{1}{t^2}\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \ge \frac{1}{\alpha_1}\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*]\right)\\
&\ge \mathrm{Prob}\left(\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \ge \frac{\beta}{\alpha_1}\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*], \frac{1}{t^2} \ge \frac{1}{\beta}\right)\\
&\ge 1 - \mathrm{Prob}\left(\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}^*] \le \frac{\beta}{\alpha_1}\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*]\right) - \mathrm{Prob}\left(\frac{1}{t^2} \le \frac{1}{\beta}\right)\\
&= 1 - \mathrm{Prob}\left(\frac{1}{t^2} \le \frac{1}{\beta}\right) > 1 - 4Q\exp\left(-\ln(5Q)\right) = 1 - 4Q/(5Q) = \frac{1}{5}.
\end{aligned}$$

In conclusion, the final approximation ratio is given by

$$\alpha_1 = \frac{8M\lambda_1(\mathbf{R})}{\mathrm{Tr}[\mathbf{R}]}\ln(5Q) = \frac{8M\lambda_1(\mathbf{R})}{\sum_{i=1}^M \lambda_i(\mathbf{R})}\ln(5Q) \le 8M\ln(5Q).$$

This completes the proof. ■

We see that if the eigenvalues of the channel covariance matrices $\mathbf{R}$ are roughly uniformly distributed, then the derived bound is of the order $\mathcal{O}(\ln(Q))$. On the other hand if $\mathbf{R}$ has a single dominant eigenvalue, then the bound is of the order $\mathcal{O}(M\ln(Q) + M)$. Nevertheless, it is important to note that the theoretical approximation ratio obtained above characterizes the quality of the *worst* solutions. As we will see later in our numerical results, in practice the proposed algorithm seems to generate solutions that have a much better quality than the derived worse-case bound.

---

[1] The cited result can be generalized from the real case to the complex case using the complex form of the large deviation results from Bernstein, see e.g., [34, Theorem 4], and the recent results by Zhang and So [32].

IV. JOINT USER SCHEDULING AND VIRTUAL BEAMFORMING

A. Problem Formulation

In this section, we consider the case where there are *two* orthogonal time slots available for transmission. The problem is to effectively allocate Q users to the first slot and the rest $M-Q$ users to the second one, so that the *minimum* SNR among these two time slots is maximized. Such min-SNR maximization problem aims at providing fairness to both groups of the users.

Let $\mathbf{w}_k \in \mathbb{C}^M$ denote the virtual beamformer used in the k-th time slot, and let $w_{k,i} \in \mathbb{C}$ denote user i's antenna gain in slot k. Mathematically, the problem is given by

$$\begin{aligned} v_2^{\mathrm{CP}} = \max_{\{\mathbf{w}_1,\mathbf{w}_2,\boldsymbol{\alpha}\}} \min_{k=1,2} \quad & \mathbf{w}_k^H \mathbf{R}(\mathbf{w}_k) \\ \text{s.t.} \quad & |w_{1,i}|^2 \le a_i P,\ |w_{2,i}|^2 \le (1-a_i)P,\ i=1,\cdots,M \\ & \sum_{i=1}^{M} a_i = Q, \quad a_i \in \{0,1\},\ i=1,\cdots,M. \end{aligned} \tag{CP2}$$

In the following, we will use $v_2^{\mathrm{CP}}(\mathbf{w}_1,\mathbf{w}_2)$ to denote the objective achieved by a feasible tuple $(\mathbf{w}_1,\mathbf{w}_2)$. Let $\mathbf{B}_0$, $\mathbf{C}_{i,0}$ and $\mathbf{C}_{i,1}$ defined the same as in (2a)–(2e). Further define

$$\begin{aligned} \bar{\mathbf{C}}_{i,0} &\triangleq \frac{1}{4}\mathbf{e}_i\mathbf{e}_i^T + \frac{1}{4}\mathbf{e}_{M+1}\mathbf{e}_{M+1}^T + \frac{1}{4}\mathbf{e}_i\mathbf{e}_{M+1}^T + \frac{1}{4}\mathbf{e}_{M+1}\mathbf{e}_i^T \in \mathbb{R}^{(M+1)\times(M+1)} \\ \mathbf{A}_{i,1} &\triangleq \mathrm{blkdg}[\mathbf{C}_{i,0},\mathbf{C}_{i,1},\mathbf{0}],\ \mathbf{A}_{i,2} \triangleq \mathrm{blkdg}[\bar{\mathbf{C}}_{i,0},\mathbf{0},\mathbf{C}_{i,1}] \in \mathbb{C}^{(3M+1)\times(3M+1)} \\ \widetilde{\mathbf{B}} &\triangleq \mathrm{blkdg}[\mathbf{B}_0,\mathbf{0},\mathbf{0}] \in \mathbb{R}^{(3M+1)\times(3M+1)} \\ \mathbf{x} &\triangleq [\mathbf{a}^T,\ell,\mathbf{w}_1^T,\mathbf{w}_2^T]^T,\ \mathbf{x}_0 \triangleq [\mathbf{a}^T,\ell],\ \mathbf{x}_1 \triangleq \mathbf{w}_1,\ \mathbf{x}_2 \triangleq \mathbf{w}_2. \end{aligned}$$

Then problem (CP2) can be equivalently written as

$$\begin{aligned} \max_{\mathbf{x}} \min_{k=1,2} \quad & \mathbf{x}_k^H \mathbf{R} \mathbf{x}_k \\ \text{s.t.} \quad & \mathbf{x}^H \mathbf{A}_{i,1} \mathbf{x} \le 1,\ i=1\cdots,M \\ & \mathbf{x}^H \mathbf{A}_{i,2} \mathbf{x} \le 1,\ i=1\cdots,M \\ & \mathbf{x}^H \widetilde{\mathbf{B}} \mathbf{x} = 4Q, \quad \mathbf{x}[i] \in \{-1,1\},\ i=1,\cdots,M+1. \end{aligned} \tag{R2}$$

B. Complexity Status

Clearly this max-min scheduling problem is at least as difficult as its admission control counterpart, as when fixing the group membership, the subproblem of maximizing per-group SNR is the same as (QP1). To see this, we again fix an index set $\mathcal{S} \subset \mathcal{M}$ with $|\mathcal{S}| = Q$, and let $\bar{\mathcal{S}} = \mathcal{M} \setminus \mathcal{S}$. Then the problem (CP2) reduces to the following two QPs, one for each slot

$$\begin{aligned} \max_{\widetilde{\mathbf{w}}_1} \quad & \widetilde{\mathbf{w}}_1^H \mathbf{R}[\mathcal{S}] \widetilde{\mathbf{w}}_1 \\ \text{s.t.} \quad & |\widetilde{\mathbf{w}}_1[i]|^2 \le P, \ i = 1, \cdots, Q \\ & \widetilde{\mathbf{w}}_1 \in \mathbb{C}^Q \end{aligned} \tag{18}$$

$$\begin{aligned} \max_{\widetilde{\mathbf{w}}_2} \quad & \widetilde{\mathbf{w}}_2^H \mathbf{R}[\bar{\mathcal{S}}] \widetilde{\mathbf{w}}_2 \\ \text{s.t.} \quad & |\widetilde{\mathbf{w}}_2[i]|^2 \le P, \ i = 1, \cdots, M-Q \\ & \widetilde{\mathbf{w}}_2 \in \mathbb{C}^{M-Q}. \end{aligned} \tag{19}$$

Clearly these problems have the same form as problem (QP1). Interestingly, unlike the admission control problem, the scheduling problem is difficult even when $\mathbf{R}$ is diagonal or is of rank 1.

Proposition 2 *Solving problem CP2 is strongly NP-hard in general.*

Proof: Below we show the case when $\mathbf{R}$ is diagonal. The claim is proved by using a polynomial time reduction from the equal partitioning with equal cardinality problem. Let M be a even number and set $Q = \frac{M}{2}$. Given a vector $\mathbf{c} \in \mathbb{R}^M$ consists of positive elements $c_1, \cdots, c_M$, let $C = \sum_{i=1}^M c_i$, the equal partitioning with equal cardinality problem finds an index set $\mathcal{I}$ with $|\mathcal{I}| = \frac{M}{2}$ such that $\frac{C}{2} = \sum_{i \in \mathcal{I}} c_i$.

Let $\mathbf{R} = \mathrm{diag}(\mathbf{c})$. We claim that determining if problem (CP2) can achieve an optimal value of $\frac{CP}{2}$ is NP-hard. Let $\mathcal{I}$ denote the set such that $\mathcal{I} = \{i : a_i = 1\}$ with $|\mathcal{I}| = \frac{M}{2}$. Then the objective of (CP2) can be written as

$$\min \left\{ \sum_{i \in \mathcal{I}} c_i |w_{1,i}|^2, \sum_{j \notin \mathcal{I}} c_j |w_{2,j}|^2 \right\} \le \min \left\{ P \sum_{i \in \mathcal{I}} c_i, P \sum_{j \notin \mathcal{I}} c_j \right\},$$

where the inequality is achieved by setting $|w_{1,i}|^2 = P, |w_{2,i}|^2 = 0, \ \forall \ i \in \mathcal{I}$, $|w_{1,i}|^2 = 0, \ |w_{2,i}|^2 = P, \ \forall \ i \notin \mathcal{I}$. Clearly, checking if we can find an index set $\mathcal{I}$ so that this problem can achieve an objective value of $\frac{CP}{2}$ is equivalent to finding a subset $\mathcal{I}$ with $|\mathcal{I}| = \frac{M}{2}$ satisfying $\frac{C}{2} = \sum_{i \in \mathcal{I}} c_i$, which is exactly the equal partitioning with equal cardinality problem.

The case when $\mathbf{R}$ is of rank 1 can be shown similarly. ■

C. The Proposed Algorithm

Define $\mathbf{X}_0 \in \mathbb{R}^{(M+1)\times(M+1)}$, $\mathbf{X}_1, \mathbf{X}_2 \in \mathbb{R}^{M \times M}$, and let $\mathbf{X} = \mathrm{blkdg}[\mathbf{X}_0, \mathbf{X}_1, \mathbf{X}_2]$. The semi-definite relaxation of problem (R2) is given by

$$v_2^{\mathrm{SDP}} = \max_{\mathbf{X} \succeq 0} \min_{k=1,2} \quad \mathrm{Tr}[\mathbf{R}\mathbf{X}_k] \tag{SDR2}$$

$$\text{s.t.} \quad \mathrm{Tr}[\mathbf{A}_{i,1}\mathbf{X}] \le 1, \ i = 1 \cdots, M \tag{20a}$$

$$\mathrm{Tr}[\mathbf{A}_{i,2}\mathbf{X}] \le 1, \ i = 1 \cdots, M \tag{20b}$$

$$\mathrm{Tr}[\widetilde{\mathbf{B}}\mathbf{X}] = 4Q \tag{20c}$$

$$\mathbf{X}[i,i] = 1, i = 1, \cdots, M+1.$$

Similarly, for a fixed index set $\mathcal{S}$, the semi-definite relaxations of problem (18) and (19) are

$$\max_{\mathbf{Y}_1 \succeq 0} \quad \text{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}_1] \tag{21a}$$

$$\text{s.t.} \quad \mathbf{Y}_1[i,i] \le P, i = 1, \cdots, Q, \tag{21b}$$

$$\max_{\mathbf{Y}_2 \succeq 0} \quad \text{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{Y}_2] \tag{21c}$$

$$\text{s.t.} \quad \mathbf{Y}_2[i,i] \le P, i = 1, \cdots, M-Q, \tag{21d}$$

The following properties are unique to the solutions for problem (SDR2).

Remark 6 Denote the events $\mathcal{A}_1(\mathbf{X})$ and $\mathcal{A}_2(\mathbf{X})$ by

$$\mathcal{A}_1(\mathbf{X}) \triangleq \{\text{all the inequalities in (20a) are tight for}\mathbf{X}\}$$
$$\mathcal{A}_2(\mathbf{X}) \triangleq \{\text{all the inequalities in (20b) are tight for } \mathbf{X}\}.$$

We claim that there must *exist* an optimal solution $\mathbf{X}^*$ for problem (CP2) such that both events $\mathcal{A}_1(\mathbf{X}^*)$ and $\mathcal{A}_2(\mathbf{X}^*)$ happens simultaneously.

We first argue that for *any* optimal solution $\mathbf{X}^*$ of (CP2), at least one of $\mathcal{A}_1(\mathbf{X}^*)$ and $\mathcal{A}_2(\mathbf{X}^*)$ is true. Assume the contrary, then there must exist at least one inequality in (20a) and one inequality in (20b) that are both inactive. Without loss of generality, assume that $\text{Tr}[\mathbf{A}_{j,1}\mathbf{X}^*] < 1$ and $\text{Tr}[\mathbf{A}_{i,2}\mathbf{X}^*] < 1$. Equivalently, we have

$$\frac{1}{P}\mathbf{X}_1^*[j,j] < \frac{1}{2}(1 + \mathbf{X}_0^*[j, M+1]), \ \frac{1}{P}\mathbf{X}_2^*[i,i] < \frac{1}{2}(1 - \mathbf{X}_0^*[i, M+1]).$$

Then there must exist two constants $\delta_1 > 0$ and $\delta_2 > 0$ such that

$$\frac{1}{P}(\mathbf{X}_1^*[j,j] + \delta_1) = \frac{1}{2}(1 + \mathbf{X}_0^*[j, M+1]), \ \frac{1}{P}(\mathbf{X}_2^*[i,i] + \delta_2) = \frac{1}{2}(1 - \mathbf{X}_0^*[i, M+1]).$$

Then $\widehat{\mathbf{X}} = \text{blkdg}[\mathbf{X}_0^*, \mathbf{X}_1^* + \mathbf{e}_j\mathbf{e}_j^T\delta_1, \mathbf{X}_2^* + \mathbf{e}_i\mathbf{e}_i^T\delta_2]$ is also feasible for problem (CP2). Moreover, the objective becomes: $\min\{\text{Tr}[\mathbf{R}(\mathbf{X}_1^* + \mathbf{e}_j\mathbf{e}_j^T\delta_1)], \text{Tr}[\mathbf{R}(\mathbf{X}_2^* + \mathbf{e}_i\mathbf{e}_i^T\delta_2)]\}$, which is strictly larger than $\min\{\text{Tr}[\mathbf{R}\mathbf{X}_1^*], \text{Tr}[\mathbf{R}\mathbf{X}_2^*]\}$. This is in contradiction to the optimality of the solution $\mathbf{X}^*$.

We then argue the claim made in the remark. Suppose for an optimal solution $\mathbf{X}^*$ and that $\mathcal{A}_1(\mathbf{X}^*)$ is true, while $\mathcal{A}_2(\mathbf{X}^*)$ is not. Then it is easy to see that the following is true

$$\min\{\text{Tr}[\mathbf{R}\mathbf{X}_1^*], \text{Tr}[\mathbf{R}\mathbf{X}_2^*]\} = \text{Tr}[\mathbf{R}\mathbf{X}_1^*]. \tag{22}$$

Otherwise one can always increase the objective without violating the constraints. Then there exist a set of constants $\delta_i \ge 0, i = 1, \cdots, M$ such that

$$\frac{1}{P}(\mathbf{X}_2^*[i,i] + \delta_i\mathbf{e}_i\mathbf{e}_i^T) = \frac{1}{2}(1 - \mathbf{X}_0^*[i, M+1])$$

while still maintaining (22). Thus, $\widetilde{\mathbf{X}} = \text{blkdg}[\mathbf{X}_0^*, \mathbf{X}_1^*, \mathbf{X}_2^* + \sum_{i=1}^{M}\delta_i\mathbf{e}_i\mathbf{e}_i^T]$ is also an optimal solution to problem (SDR2). The remaining case when $\mathcal{A}_2(\mathbf{X}^*)$ is true and $\mathcal{A}_1(\mathbf{X}^*)$ is not can be argued similarly.

Remark 7 At optimality, the property for the sum of the last column of $\mathbf{X}_0^*$ in Remark 3 still holds true. Further, suppose for an optimal solution $\mathbf{X}^*$ both events $\mathcal{A}_1(\mathbf{X}^*)$ and $\mathcal{A}_2(\mathbf{X}^*)$ are true. Then we have the following

$$\sum_{i=1}^{M}\mathbf{X}_1^*[i,i]=\frac{P}{2}\sum_{i=1}^{M}(1+\mathbf{X}_0^*[i,M+1])=\frac{P}{2}(M+(2Q-M))=PQ \tag{23}$$

$$\sum_{i=1}^{M}\mathbf{X}_2^*[i,i]=\frac{P}{2}\sum_{i=1}^{M}(1-\mathbf{X}_0^*[i,M+1])=\frac{P}{2}(M-(2Q-M))=P(M-Q). \tag{24}$$

To formally describe the proposed algorithm, the following definitions are needed. Decompose $\mathbf{X}_1^*$, $\mathbf{X}_2^*$ by $\mathbf{X}_1^*=\mathbf{\Delta}_1^H\mathbf{\Delta}_1$ and $\mathbf{X}_2^*=\mathbf{\Delta}_2^H\mathbf{\Delta}_2$, respectively. Let $\mathcal{S}\subseteq\mathcal{M}$ be any index set, define the following

$$\mathbf{E}_i(\mathcal{S},\mathbf{\Delta}_k)\triangleq\mathbf{\Delta}_k\mathbf{C}_{i,1}[\mathcal{S}]\mathbf{\Delta}_k^H,\ \mathbf{E}(\mathcal{S},\mathbf{\Delta}_k)\triangleq\mathbf{\Delta}_k\mathbf{R}[\mathcal{S}]\mathbf{\Delta}_k^H.$$

Let us decompose $\mathbf{E}(\mathcal{S},\mathbf{\Delta}_k)$ using its eigendecomposition

$$\mathbf{E}(\mathcal{S},\mathbf{\Delta}_k)=\mathbf{U}(\mathcal{S},\mathbf{\Delta}_k)\mathbf{\Sigma}(\mathcal{S},\mathbf{\Delta}_k)\mathbf{U}^H(\mathcal{S},\mathbf{\Delta}_k). \tag{25}$$

Then the diagonal matrix $\mathbf{\Sigma}(\mathcal{S},\mathbf{\Delta}_k)$ can be expressed as

$$\mathbf{\Sigma}(\mathcal{S},\mathbf{\Delta}_k)=\mathbf{U}^H(\mathcal{S},\mathbf{\Delta}_k)\mathbf{E}(\mathcal{S},\mathbf{\Delta}_k)\mathbf{U}(\mathcal{S},\mathbf{\Delta}_k)=\mathbf{U}^H(\mathcal{S},\mathbf{\Delta}_k)\mathbf{\Delta}_k\mathbf{R}[\mathcal{S}]\mathbf{\Delta}_k^H\mathbf{U}(\mathcal{S},\mathbf{\Delta}_k). \tag{26}$$

Further define $\widehat{\mathbf{E}}_i(\mathcal{S},\mathbf{\Delta}_k)\triangleq\mathbf{U}^H(\mathcal{S},\mathbf{\Delta}_k)\mathbf{E}_i(\mathcal{S},\mathbf{\Delta}_k)\mathbf{U}(\mathcal{S},\mathbf{\Delta}_k)$.

The proposed algorithm is listed in Table II. It has similar steps as the admission control algorithm. The main difference is that after deciding the set $\mathcal{S}$, *two* separate SDPs need to be solved, one for each set $\mathcal{S}$ and $\bar{\mathcal{S}}$. The final solutions $\mathbf{w}_1^*$ and $\mathbf{w}_2^*$ are then obtained using the randomized algorithm base on the solutions of these two SDPs. Note that to find a solution required by Step S1), we can start by any optimal solution $\mathbf{X}^*$ of (SDR2), and increase the diagonal elements of $\mathbf{X}_1^*$ or $\mathbf{X}_2^*$ until all the constraints in (20a) and (20b) are satisfied.

Using the argument identical to that presented in Remark 4 and Remark 5, we can verify that for all ℓ, $[\mathbf{x}_0,\mathbf{w}_1^{(\ell)},\mathbf{w}_2^{(\ell)}]$ must be feasible for problem (R2). Moreover, we have that

$$(\mathbf{w}_1^{(\ell)})^H\mathbf{R}\mathbf{w}_1^{(\ell)}=\frac{1}{(t_1^{(\ell)})^2}\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}_1^*],\ (\mathbf{w}_2^{(\ell)})^H\mathbf{R}\mathbf{w}_2^{(\ell)}=\frac{1}{(t_2^{(\ell)})^2}\mathrm{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{Y}_2^*].$$

D. The Approximation Bounds

We have the following results regarding to the quality of the solution $\mathbf{x}^*$.

Theorem 2 *If $\mathbf{x}^*$ is generated according to the algorithm listed in Table II, then $v_2^{\mathrm{CP}}(\mathbf{w}_1^*,\mathbf{w}_2^*)\ge\frac{1}{\alpha_2}v_2^{\mathrm{SDP}}$, with α_2 given as*

$$\alpha_2=\frac{8M\lambda_1(\mathbf{R})}{\min\{Q,M-Q\}\lambda_M(\mathbf{R})}\ln(12\max\{Q,M-Q\}). \tag{27}$$

TABLE II
THE PROPOSED ALGORITHM FOR JOINT BEAMFORMING AND SCHEDULING

```
S1: Compute the optimal solution $\mathbf{X}^*$ of problem (SDR2),
    such that all the constraints in (20a) and (20b) are tight.
S2: Find a set $\mathcal{S}$ of indices such that $|\mathcal{S}| = Q$ and
        $\mathcal{S} = \{j : \mathbf{X}_0^*[j, M+1] \geq \underline{\mathbf{x}}_{(Q)}\}$
    Set $\bar{\mathcal{S}} = \mathcal{M} \setminus \mathcal{S}$;
S3: Set $\mathbf{x}_0[M+1] = 1$ and $\mathbf{x}_0[j] = 1$, for all $j \in \mathcal{S}$;
    Set $\mathbf{x}_0[i] = -1$ for all $i \in \bar{\mathcal{S}}$;
S4: Compute the solution $\mathbf{Y}_1^*$, $\mathbf{Y}_2^*$ of problem (18) and (19),
    with index sets $\mathcal{S}$ and $\bar{\mathcal{S}}$, respectively;
For $\ell = 1, \cdots, L$
S5: Generate $\boldsymbol{\xi}_1^{(\ell)} \in \{-1,1\}^Q$ and $\boldsymbol{\xi}_2^{(\ell)} \in \{-1,1\}^{M-Q}$ by randomly and
    independently generating their components uniformly from $\{-1,1\}$;
S6: Compute $t_1^{(\ell)} = \sqrt{\max_{i\in\mathcal{S}} (\boldsymbol{\xi}_1^{(\ell)})^T \widehat{\mathbf{E}}_i(\mathcal{S}, \boldsymbol{\Delta}_1) \boldsymbol{\xi}_1^{(\ell)}}$;
    Compute $t_2^{(\ell)} = \sqrt{\max_{i\in\bar{\mathcal{S}}} (\boldsymbol{\xi}_2^{(\ell)})^T \widehat{\mathbf{E}}_i(\bar{\mathcal{S}}, \boldsymbol{\Delta}_2) \boldsymbol{\xi}_2^{(\ell)}}$;
S7: Compute  $\widetilde{\mathbf{w}}_1^{(\ell)} = \frac{1}{t_1^{(\ell)}} \boldsymbol{\Delta}_1^H \mathbf{U}(\mathcal{S}, \boldsymbol{\Delta}_1) \boldsymbol{\xi}_1^{(\ell)}$;
             $\widetilde{\mathbf{w}}_2^{(\ell)} = \frac{1}{t_2^{(\ell)}} \boldsymbol{\Delta}_2^H \mathbf{U}(\bar{\mathcal{S}}, \boldsymbol{\Delta}_2) \boldsymbol{\xi}_2^{(\ell)}$;
    Let $\mathbf{w}_1^{(\ell)}[\mathcal{S}] = \widetilde{\mathbf{w}}_1^{(\ell)}$, $\mathbf{w}_1^{(\ell)}[\bar{\mathcal{S}}] = \mathbf{0}$;
    Let $\mathbf{w}_2^{(\ell)}[\bar{\mathcal{S}}] = \widetilde{\mathbf{w}}_2^{(\ell)}$, $\mathbf{w}_2^{(\ell)}[\mathcal{S}] = \mathbf{0}$;
End For
S8: Set $\ell^* = \arg_\ell \max_\ell \min\{(\mathbf{w}_1^{(\ell)})^H \mathbf{R} \mathbf{w}_1^{(\ell)}, (\mathbf{w}_2^{(\ell)})^H \mathbf{R} \mathbf{w}_2^{(\ell)}\}$;
    Set $\mathbf{w}_1^* = \mathbf{w}_1^{(\ell^*)}$, $\mathbf{w}_2^* = \mathbf{w}_2^{(\ell^*)}$, $\mathbf{x}^* = [\mathbf{x}_0^T, (\mathbf{w}_1^*)^T, (\mathbf{w}_2^*)^T]^T$;
```

Proof: The proof of this theorem follows the similar steps as in Section III-E. Again our goal is to show that there exits a $\delta > 0$ such that

$$\text{Prob}\left(\min_{k=1,2}\{(\mathbf{w}_k^{(\ell)})^H \mathbf{R} \mathbf{w}_k^{(\ell)}\} \geq \frac{1}{\alpha_2} \min_{k=1,2}\{\text{Tr}[\mathbf{R}\mathbf{X}_k^*]\}\right) \geq \delta > 0.$$

Note that we have

$$\begin{aligned}
&\text{Prob}\left(\min_{k=1,2}\{(\mathbf{w}_k^{(\ell)})^H \mathbf{R} \mathbf{w}_k^{(\ell)}\} \geq \frac{1}{\alpha_2} \min_{k=1,2}\{\text{Tr}[\mathbf{R}\mathbf{X}_k^*]\}\right) \\
&= \text{Prob}\left(\min\left\{\frac{1}{(t_1^{(\ell)})^2}\text{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}_1^*], \frac{1}{(t_2^{(\ell)})^2}\text{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{Y}_2^*]\right\} \geq \frac{1}{\alpha_2} \min_{k=1,2}\{\text{Tr}[\mathbf{R}\mathbf{X}_k^*]\}\right) \\
&\geq \text{Prob}\left(\min\left\{\text{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}_1^*], \text{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{Y}_2^*]\right\} \geq \frac{\beta}{\alpha_2} \min_{k=1,2}\{\text{Tr}[\mathbf{R}\mathbf{X}_k^*]\}, \frac{1}{(t_1^{(\ell)})^2} \geq \frac{1}{\beta}, \frac{1}{(t_2^{(\ell)})^2} \geq \frac{1}{\beta}\right).
\end{aligned}$$

We first lower bound $\text{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{Y}_2^*]$ as follows

$$\text{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{Y}_2^*] \geq \text{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{X}_2^*[\bar{\mathcal{S}}]] = \text{Tr}[\boldsymbol{\Omega}(\bar{\mathcal{S}})\mathbf{R}\boldsymbol{\Omega}(\bar{\mathcal{S}})\mathbf{X}_2^*]$$

where the inequality is from the optimality of $\mathbf{Y}_2^*$ as well as the feasibility of $\mathbf{X}_2^*[\bar{\mathcal{S}}]$ to the problem (19). The right hand side of the above inequality can be further lower bounded by

$$\begin{aligned}
&\mathrm{Tr}[\mathbf{\Omega}(\bar{\mathcal{S}})\mathbf{R}\mathbf{\Omega}(\bar{\mathcal{S}})\mathbf{X}_2^*] \geq \mathrm{Tr}[\mathbf{\Omega}(\bar{\mathcal{S}})\mathbf{X}_2^*\mathbf{\Omega}(\bar{\mathcal{S}})]\lambda_M(\mathbf{R}) = \sum_{i\in\bar{\mathcal{S}}}\mathbf{X}_2^*[i,i]\lambda_M(\mathbf{R})\\
&\overset{\text{(i)}}{=} \frac{P\lambda_M(\mathbf{R})}{2}\left(M-Q-\sum_{i\in\bar{\mathcal{S}}}\mathbf{X}_0^*[i,M+1]\right)\\
&\overset{\text{(ii)}}{\geq} \frac{P\lambda_M(\mathbf{R})}{2}\left(M-Q-\frac{(M-Q)Q}{M}\right) = \frac{P(M-Q)^2}{M}\lambda_M(\mathbf{R}).
\end{aligned} \tag{28}$$

where (i) is because of the tightness of the constraint (20b). We argue the inequality (ii) as follows. Due to Step S2) of the algorithm, $\{\mathbf{X}_0^*[i,M+1]\}_{i\in\bar{\mathcal{S}}}$ are the *smallest* $M-Q$ elements in $\{\mathbf{X}_0^*[i,M+1]\}_{i=1}^M$. Combining with the fact that $\sum_{i=1}^M\mathbf{X}_0^*[i,M+1]=Q$, we must have that $\sum_{i\in\bar{\mathcal{S}}}\mathbf{X}_0^*[i,M+1]\leq\frac{M-Q}{M}Q$, which further implies (b). Combining the above two inequalities, we obtain $\mathrm{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{Y}_2^*]\geq\frac{P(M-Q)^2}{M}\lambda_M(\mathbf{R})$.

Using the same argument, we can lower bound $\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}_1^*]$ by: $\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}_1^*]\geq\frac{Q^2P}{M}\lambda_M(\mathbf{R})$. As a result, we have

$$\min\left\{\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{Y}_1^*],\mathrm{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{Y}_2^*]\right\}\geq\min\{Q^2,(M-Q)^2\}\frac{P}{M}\lambda_M(\mathbf{R}).$$

Utilizing the results in Remark 7, we further have

$$\begin{aligned}
\mathrm{Tr}[\mathbf{R}\mathbf{X}_1^*]&\leq\lambda_1(\mathbf{R})\mathrm{Tr}[\mathbf{X}_1^*]=\lambda_1(\mathbf{R})QP\\
\mathrm{Tr}[\mathbf{R}\mathbf{X}_2^*]&\leq\lambda_1(\mathbf{R})\mathrm{Tr}[\mathbf{X}_2^*]=\lambda_1(\mathbf{R})P(M-Q)
\end{aligned}$$

which implies $\min_{k=1,2}\{\mathrm{Tr}[\mathbf{R}\mathbf{X}_k^*]\}\leq\lambda_1(\mathbf{R})P\min\{Q,M-Q\}$. Consequently, when choosing

$$\frac{\beta}{\alpha_2}=\frac{\lambda_1(\mathbf{R})P\min\{Q,M-Q\}}{\min\{Q^2,(M-Q)^2\}P\frac{Q}{M}\lambda_M(\mathbf{R})}=\frac{\lambda_1(\mathbf{R})M}{\lambda_M(\mathbf{R})\min\{Q,M-Q\}}$$

we have

$$\mathrm{Prob}\left(\min\left\{\mathrm{Tr}[\mathbf{R}[\mathcal{S}]\mathbf{X}_1^*],\mathrm{Tr}[\mathbf{R}[\bar{\mathcal{S}}]\mathbf{X}_2^*]\right\}<\frac{\beta}{\alpha_2}\min_{k=1,2}\{\mathrm{Tr}[\mathbf{R}\mathbf{X}_k^*]\}\right)=0.$$

Going through similar steps as in Step 2)–Step 3) in the proof of Theorem 1, the final ratio is

$$\alpha_2=\frac{8M\lambda_1(\mathbf{R})}{\min\{Q,M-Q\}\lambda_M(\mathbf{R})}\ln(12\max\{Q,M-Q\}). \tag{29}$$

This completes the proof. ■

Clearly for a given channel covariance $\mathbf{R}$, the bound developed above achieves its minimum when the two slots have the same number of users, i.e., when $M=2Q$. On the other hand, the ratio becomes worse if the the number of users allocated to the slots are increasingly unbalanced. We mention that it is possible to extend our approach to scenarios when multiple orthogonal time-slots are available. However, unlike the 2-slot case, more discrete variables are required (M discrete variables for each slot). Our current algorithm and its approximation bound need to be carefully modified for this more complicated case. We leave this problem as a future research direction.

V. JOINT RELAY GROUPING AND VIRTUAL BEAMFORMING

The approaches we have developed in the previous sections are applicable to a more general relay network, where the problem is to group the relays to form a virtual multi-antenna system, and at the same time design their virtual beamformers for optimal signal relaying.

A. System Model

Consider a network with a pair pair of transceiver and a set of M relays, each of which has a single antenna (see Fig. 2 for an illustration). Assume that there is no direct link between the transmitter and the receiver. Let $\{f_i\}_{i=1}^M$ and $\{g_i\}_{i=1}^M$ denote the complex channel coefficients between the user and the relays, and between the relays and the receiver, respectively.

Let us focus on a popular AF relay protocol, in which the transmitter broadcasts the desired signal to the relays, who subsequently forward the signals to the receiver. Assume that there is a large number of relays available, and any group of them can form a virtual multi-antenna system for transmission. For the same reason as in the user grouping problem such as overhead reduction and synchronization, it is of interest to select a subset of relays to joint the AF process.

To formally present the system model, we use $s \in \mathbb{C}$ to denote the message transmitted by the transmitter; use P_0 to denote the transmit power; use ν_i to denote the noise at the i-th relay with power σ_ν^2. Then the signal x_i received at the i-th relay can be expressed as $x_i = \sqrt{P_0} f_i s + \nu_i$. Again use w_i to denote the complex gain applied by the i-th relay, it follows that the transmitted signal of i-th relay is given by $y_i = w_i x_i$. Using this expression, we readily obtain the averaged transmit power of relay i

$$\mathbb{E}[|y_i|^2] = |w_i|^2 \mathbb{E}[x_i \bar{x}_i] = |w_i|^2 \left(P_0 \mathbb{E}[|f_i|^2] + \sigma_\nu^2\right).$$

Let $n \in \mathcal{CN}(0, \sigma_n^2)$ denote the noise at the receiver, then the received signal is given by

$$z = \sum_{i=1}^M g_i y_i + n = \underbrace{\sqrt{P_0} \sum_{i=1}^M w_i f_i g_i s}_{\text{signal}} + \underbrace{\sum_{i=1}^M w_i g_i \nu_i + n}_{\text{noise}}. \tag{30}$$

The averaged signal power at the receiver is then given by

$$\mathbb{E}\left[\left|\sqrt{P_0} \sum_{i=1}^M w_i f_i g_i s\right|^2\right] = \mathbf{w}^H \mathbf{S} \mathbf{w} \tag{31}$$

where $\mathbf{S} \triangleq P_0 \mathbb{E}[(\mathbf{f} \bigodot \mathbf{g})(\mathbf{f} \bigodot \mathbf{g})^H]$, with $\bigodot$ denoting the componentwise product. Assuming $\{\nu_i\}_{i=1}^M$ and $\{g_i\}_{i=1}^M$ are independent from each other, the averaged noise power is given by [11]

$$\mathbb{E}\left[\left|\sum_{i=1}^M w_i g_i \nu_i + n\right|^2\right] = \mathbf{w}^H \mathbf{F} \mathbf{w} + \sigma_n^2, \tag{32}$$

where $\mathbf{F} \triangleq \mathbb{E}[(\mathbf{g} \bigodot \boldsymbol{\nu})(\mathbf{g} \bigodot \boldsymbol{\nu})^H]$. Additionally, if we further assume that the noises $\{\nu_i\}_{i=1}^M$ are independent, then $\mathbf{F}$ becomes diagonal: $\mathbf{F} \triangleq \sigma_\nu^2 \mathrm{diag}(\mathbb{E}[\mathbf{g}\mathbf{g}^H])$. It follows that the averaged SNR at the receiver is given by [11]: $\mathrm{SNR} = \frac{\mathbf{w}^H\mathbf{S}\mathbf{w}}{\sigma_n^2+\mathbf{w}^H\mathbf{F}\mathbf{w}}$. The joint relay grouping and beamforming problem can be formulated as

$$\begin{aligned} v_3^{\mathrm{CP}} = \max_{\mathbf{w},\mathbf{a}} \quad & \frac{\mathbf{w}^H\mathbf{S}\mathbf{w}}{\sigma_n^2 + \mathbf{w}^H\mathbf{F}\mathbf{w}} \\ \mathrm{st} \quad & |w_i|^2\left(P_0\mathbb{E}[|f_i|^2] + \sigma_\nu^2\right) \le a_i P,\ i = 1, \cdots, M, \\ & \sum_{i=1}^M a_i = Q,\ a_i \in \{0,1\},\ i = 1, \cdots, M. \end{aligned} \tag{CP3}$$

Once again, we have used the variables $\mathbf{a} = [a_1, \cdots, a_M] \in \{0,1\}^M$ to denote the binary grouping decisions. This problem can be compactly written as

$$\begin{aligned} v_3^{\mathrm{QP}} = \max_{\mathbf{x}} \quad & \frac{\mathbf{x}^H\widetilde{\mathbf{S}}\mathbf{x}}{\sigma_n^2 + \mathbf{x}^H\widetilde{\mathbf{F}}\mathbf{x}} && \text{(R3)} \\ \mathrm{s.t.} \quad & \mathbf{x}^H\mathbf{D}_i\mathbf{G}_i\mathbf{x} \le 1,\ i = 1, \cdots, M, && \text{(33a)} \\ & \mathbf{x}^H\mathbf{B}\mathbf{x} = 4Q,\ \mathbf{x}[i] \in \{-1,1\},\ i = 1, \cdots, M+1. && \text{(33b)} \end{aligned}$$

where $\mathbf{D}_i$, $\mathbf{B}$ and $\mathbf{x}$ are given in (2a)–(2e), and the $(2M+1)\times(2M+1)$ matrices $\widetilde{\mathbf{F}}$, $\widetilde{\mathbf{S}}$ and $\mathbf{G}_i$ are defined as

$$\begin{aligned} & \widetilde{\mathbf{S}} \triangleq \begin{bmatrix} \mathbf{0} & \mathbf{0} \\ \mathbf{0} & \mathbf{S} \end{bmatrix},\ \widetilde{\mathbf{F}} \triangleq \begin{bmatrix} \mathbf{0} & \mathbf{0} \\ \mathbf{0} & \mathbf{F} \end{bmatrix}, \\ & \mathbf{G}_i \triangleq \begin{bmatrix} \mathbf{I_{M+1}} & \mathbf{0} \\ \mathbf{0} & \mathbf{e}_i\mathbf{e}_i^T\left(P_0\mathbb{E}[|f_i|^2] + \sigma_\nu^2\right) \end{bmatrix},\ i = 1, \cdots, M. \end{aligned}$$

B. The Complexity Status

In this subsection, we analyze the numerical complexity of joint relay grouping and virtual beamforming problem. The following theorem shows that solving (CP3) is generally NP-hard.

Theorem 3 *Solving* (CP3) *is NP-hard in general.*

Proof: It suffices to show that solving (CP3) is NP-hard even when the active relays are known. In other words, it is sufficient to show that solving the problem

$$\begin{aligned} \max_{\mathbf{w}} \quad & \frac{\mathbf{w}^H\mathbf{S}\mathbf{w}}{\sigma_n^2 + \mathbf{w}^H\mathbf{F}\mathbf{w}} \\ \mathrm{s.t.} \quad & |w_i|^2\left(P_0\mathbb{E}[|f_i|^2] + \sigma_\nu^2\right) \le P,\ i = 1, \cdots, M, \end{aligned} \tag{35}$$

is NP-hard. We prove by using a polynomial time reduction from the integer equal partitioning problem. To this end, let us consider the following system parameters:

$$P_0 = 1, \quad P = 2, \quad \sigma_v^2 = 1, \quad f_i = 1, \forall i.$$

Then the problem (35) can equivalently be written as

$$\begin{aligned} \max_{\mathbf{w}} \quad & \frac{\mathbf{w}^H \mathbb{E}[\mathbf{g}\mathbf{g}^H]\mathbf{w}}{\sigma_n^2 + \mathbf{w}^H \mathrm{diag}\left(\mathbb{E}[\mathbf{g}\mathbf{g}^H]\right)\mathbf{w}} \\ \text{s.t.} \quad & |w_i|^2 \le 1, \ i = 1, \cdots, M. \end{aligned} \tag{36}$$

Let t denote the objective value of the above problem. In order to check the achievability of a particular value t, we need to check the feasibility of the following set of inequalities:

$$\begin{aligned} & \mathbf{w}^H \left(\mathbb{E}[\mathbf{g}\mathbf{g}^H] - t\mathrm{diag}\left(\mathbb{E}[\mathbf{g}\mathbf{g}^H]\right)\right)\mathbf{w} \ge t\sigma_n^2 \\ & |w_i|^2 \le P, \quad \forall i. \end{aligned} \tag{37}$$

Therefore, it suffices to show the NP-hardness of checking the achievability of (37). To this end, we first claim that for given a positive definite matrix $\mathbf{A}$, the following set is non-empty

$$\mathcal{T} = \left\{(t, \mathbf{X}) \mid \mathbf{X} - t\mathrm{diag}(\mathbf{X}) = \mathbf{A}, \mathbf{A} \succ 0, t > 0, t \in \mathbb{R}, \mathbf{X} \in \mathbb{R}^{M\times M}\right\}$$

To justify this claim, consider the mapping $\phi_{\mathbf{A}}(t) : \mathbb{R}^+ \mapsto \mathbb{R}^{M\times M}$, where $\phi_{\mathbf{A}}(t) = \mathbf{B}$ with

$$\mathbf{B}_{ij} = \begin{cases} \mathbf{A}_{ij} & i \neq j \\ \frac{\mathbf{A}_{ii}}{1-t} & i = j \end{cases}.$$

Note that $\phi_{\mathbf{A}}(t)$ is continuous over $[0, 1)$ and $\phi_{\mathbf{A}}(0) = \mathbf{A}$. Therefore, for small enough $t' > 0$, we have $\phi_{\mathbf{A}}(t') = \mathbf{B}' \succ 0$. In other words, $(t', \mathbf{B}') \in \mathcal{T}$. The above claim implies that there exists a positive definite matrix $\mathbf{R} = \mathbb{E}[\mathbf{g}\mathbf{g}^H]$ and a positive scalar t such that

$$\mathbb{E}[\mathbf{g}\mathbf{g}^H] - t\mathrm{diag}\left(\mathbb{E}[\mathbf{g}\mathbf{g}^H]\right) = 2C\mathbf{I} - \mathbf{c}\mathbf{c}^T,$$

with $C = \|\mathbf{c}\|^2$. Therefore, using the similar argument to the one in the proof of Proposition 1 completes the proof. ■

Unlike the general case, problem (CP3) is easy when there is no correlation between the channels, i.e., when the matrices $\mathbf{S}$ and $\mathbf{F}$ are both diagonal. In fact, for a fixed value of t, checking the feasibility problem

$$\begin{aligned} & \frac{\mathbf{w}^H\mathbf{S}\mathbf{w}}{\sigma_n^2 + \mathbf{w}^H\mathbf{F}\mathbf{w}} \ge t \\ & |w_i|^2 \left(P_0\mathbb{E}(|f_i|^2) + \sigma_v^2\right) \le a_i P, \ \forall i \\ & \sum_{i=1}^{M} a_i = Q, \quad a_i \in \{0, 1\} \end{aligned}$$

is easy since we only need to pick the Q largest positive diagonal elements of $\mathbf{S} - t\mathbf{F}$ and set the corresponding $a_i = 1$. Using this observation and performing a bisection procedure on t, we can obtain the optimal solution for (CP3). In conclusion, (CP3) is polynomial time solvable when both $\mathbf{S}$ and $\mathbf{F}$ are diagonal.

Similar to problem (CP2), one can consider the relay scheduling problem over two time slots. Mathematically, this problem can be formulated as

$$\begin{aligned} \max_{\{\mathbf{w}_1,\mathbf{w}_2,\boldsymbol{\alpha}\}} \min_{k=1,2} \quad & \frac{\mathbf{w}_k^H \mathbf{S} \mathbf{w}_k}{\sigma_n^2 + \mathbf{w}_k^H \mathbf{F} \mathbf{w}_k} \\ \text{s.t.} \quad & |w_{1,i}|^2 \left(P_0 \mathbb{E}[|f_i|^2] + \sigma_v^2\right) \leq a_i P,\ |w_{2,i}|^2 \left(P_0 \mathbb{E}[|f_i|^2] + \sigma_v^2\right) \leq (1-a_i)P,\ i = 1, \cdots, M \\ & \sum_{i=1}^{M} a_i = Q, \quad a_i \in \{0,1\},\ i = 1, \cdots, M. \end{aligned} \tag{CP4}$$

It turns out that this problem is NP-hard even for the special case of diagonal channel correlation.

Theorem 4 *For diagonal channel correlation matrices, problem* (CP4) *is NP-hard.*

Proof: Assume that $f_i = 1, \forall i$. It suffices to show that checking the feasibility problem

$$\begin{aligned} & \min_{k=1,2} \frac{\mathbf{w}_k^H \mathbb{E}(\mathbf{g}\mathbf{g}^H) \mathbf{w}_k}{\sigma_n^2 + \mathbf{w}_k^H \operatorname{diag}\left(\mathbb{E}[\mathbf{g}\mathbf{g}^H]\right) \mathbf{w}_k} \geq t \\ & |w_{1,i}|^2 \left(P_0 \mathbb{E}[|f_i|^2] + \sigma_v^2\right) \leq a_i P,\ |w_{2,i}|^2 \left(P_0 \mathbb{E}[|f_i|^2] + \sigma_v^2\right) \leq (1-a_i)P,\ i = 1, \cdots, M \\ & \sum_{i=1}^{M} a_i = Q, \quad a_i \in \{0,1\},\ i = 1, \cdots, M, \end{aligned} \tag{38}$$

is NP-hard. Let us also consider the following system parameters:

$$\mathbb{E}[|g_i|^2] = c_i > 0, \quad P_0 = \sigma_v^2 = 1, \quad P = 2, \quad Q = \frac{M}{2}, \quad t = \frac{1}{2}.$$

Using these parameters, the feasibility problem (38) can be simplified as

$$\begin{aligned} & \frac{\sum |w_{k,i}|^2 c_i}{\sigma_n^2 + \sum |w_{k,i}|^2 c_i} \geq \frac{1}{2}, \quad k = 1, 2 \\ & |w_{1,i}|^2 \leq a_i,\ |w_{2,i}|^2 \leq (1 - a_i),\ i = 1, \cdots, M \\ & \sum_{i=1}^{M} a_i = \frac{M}{2}, \quad a_i \in \{0,1\},\ i = 1, \cdots, M \end{aligned}$$

Set $\sigma_n^2 = \sum_i c_i / 2$. Using the above parameters, one can easily show that problem (39) is feasible iff the following NP-complete equal partitioning with equal cardinality problem is feasible: *Find an index set* $\mathcal{I} \subseteq \{1, 2, \ldots, M\}$ *with* $|\mathcal{I}| = \frac{M}{2}$ *such that* $\sum_{i \in \mathcal{I}} c_i = \sum_{i \in \bar{\mathcal{I}}^c} c_i$.
Such equivalence completes the proof. ■

C. The Algorithm

Again let us define $\mathbf{X} \triangleq \mathbf{x}\mathbf{x}^H$. The semi-definite relaxation of the reformulated problem (R3) is given by

$$v_3^{\mathrm{SDP}} \triangleq \max_{\mathbf{X}\succeq 0} \quad \frac{\mathrm{Tr}[\widetilde{\mathbf{S}}\mathbf{X}]}{\sigma_n^2 + \mathrm{Tr}[\widetilde{\mathbf{F}}\mathbf{X}]} \tag{SDP3}$$

$$\text{s.t.} \quad \mathrm{Tr}[\mathbf{D}_i\mathbf{G}_i\mathbf{X}] \le 1, \ i = 1, \cdots, M, \tag{39a}$$

$$\mathrm{Tr}[\mathbf{B}\mathbf{X}] = 4Q, \tag{39b}$$

$$\mathbf{X}[i,i] = 1, \ i = 1, \cdots, M+1. \tag{39c}$$

Let $\mathbf{X}^*$ denote the optimal solution of this problem. Clearly, we must have $\mathrm{Tr}[\widetilde{\mathbf{S}}\mathbf{X}^*] = v_3^{\mathrm{SDP}}(\sigma_n^2 + \mathrm{Tr}[\widetilde{\mathbf{F}}\mathbf{X}^*])$. Moreover, $\mathbf{X}^*$ must be the optimal solution of the following problem, with an optimal objective value $v_3^{\mathrm{SDP}}\sigma_n^2$

$$\max_{\mathbf{X}\succeq 0} \quad \mathrm{Tr}[(\widetilde{\mathbf{S}} - v_3^{\mathrm{SDP}}\widetilde{\mathbf{F}})\mathbf{X}] \tag{SDP4}$$

$$\text{s.t.} \quad \text{(39a) – (39c)}.$$

This problem is a relaxation of the following QP

$$\max_{\mathbf{x}} \quad \mathbf{x}^H(\widetilde{\mathbf{S}} - v_3^{\mathrm{SDP}}\widetilde{\mathbf{F}})\mathbf{x}$$

$$\text{s.t.} \quad \text{(33a) – (33b)}.$$

The similarity between problem (SDP4) and the relaxed user selection problem (SDP1) suggests a natural two-step approach for obtaining a feasible solution $\mathbf{x}^*$ of (R3):

1) Solve problem (SDP3), obtain v_3^{SDP}.
2) Obtain $\mathbf{x}^* = [\mathbf{x}_0^*, \mathbf{w}^*]$ by applying the algorithm in Table I, with the matrices $\widetilde{\mathbf{R}}$, $\mathbf{D}_i$ replaced by $\widetilde{\mathbf{S}} - v_3^{\mathrm{SDP}}\widetilde{\mathbf{F}}$, $\mathbf{D}_i\mathbf{G}_i$, respectively.

Using the same argument given in Remark 5, we can show that the resulting vector $\mathbf{x}^*$ must be feasible for our relay selection problem.

Remark 8 If we can show that $\mathbf{x}^*$ achieves a $\frac{1}{\alpha_3}$ fraction of the optimal value of problem (SDP4), then it follows that

$$(\mathbf{w}^*)^H(\mathbf{S} - v_3^{\mathrm{SDP}}\mathbf{F})\mathbf{w}^* = (\mathbf{x}^*)^H(\widetilde{\mathbf{S}} - v_3^{\mathrm{SDP}}\widetilde{\mathbf{F}})\mathbf{x}^* \ge \frac{1}{\alpha_3}\mathrm{Tr}[(\widetilde{\mathbf{S}} - v_3^{\mathrm{SDP}}\widetilde{\mathbf{F}})\mathbf{X}^*] = \frac{\sigma_n^2 v_3^{\mathrm{SDP}}}{\alpha_3}.$$

Using the fact that $\alpha_3 > 1$ and that $(\mathbf{w}^*)^H\mathbf{F}\mathbf{w}^* > 0$, we obtain

$$v_3^{\mathrm{CP}}(\mathbf{w}^*) = \frac{(\mathbf{x}^*)^H\mathbf{S}\mathbf{x}^*}{\sigma_n^2 + v^{\mathrm{SDP}}(\mathbf{x}^*)^H\mathbf{F}\mathbf{x}^*} \ge \frac{1}{\alpha_3}v_3^{\mathrm{SDP}}.$$

which says that $\mathbf{w}^*$ is also an α_3-approximated solution for problem (CP3).

Unfortunately, to this point we are not able to obtain a formal approximation bound for the solutions so obtained. The main difficulty is that, unlike in problem (SDP1), the coefficient matrix $\widetilde{\mathbf{S}} - v_3^{\mathrm{SDP}}\widetilde{\mathbf{F}}$ in the objective of (SDP4) is no longer a positive definite matrix (in fact, it is an indefinite matrix). Consequently, key properties of the solution for the (SDP1) that guarantee the existence of the lower/upper bounds of the objective value such as those described in Remark 2 no longer hold true in this case.

Nevertheless, in our numerical experiment, we observe that the algorithm proposed in this section generates high quality approximated solutions for problem (CP3).

VI. NUMERICAL RESULTS

In this section, we conduct numerical experiments to evaluate the proposed algorithms. For all simulations presented, we choose the total number of randomization as $L = 200$.

A. *Grouping for Admission Control and Scheduling*

We evaluate the performance of the proposed algorithm for joint admission control and beamforming. Let $N > 0$ be a constant, which represents the number of antennas at the receiver. We model the channels as following the Rayleigh distribution, and generate the channel matrix $\mathbf{R}$ as follows: 1) generate the entries of a matrix $\widehat{\mathbf{H}} \in \mathbb{C}^{M\times N}$ i.i.d from a standard complex Gaussian distribution; 2) set $\mathbf{R} = \widehat{\mathbf{H}}\widehat{\mathbf{H}}^H \succeq 0$. Consider a network with $M = 30$ users with each user having the same transmit power. Let the total transmission power of the users, denoted as P_{tot}, set to be $P_{\mathrm{tot}} = 10$ dBW. The proposed algorithm in Section III (abbreviated as Al. 1) is compared with a sparse PCA based algorithm, whose main steps are listed below: *i)* Approximately find a *sparse* principal component of $\mathbf{R}$ with Q non-zero entries (denoted as $\widehat{\mathbf{w}}$), using the backward-forward algorithm proposed in [29]; *ii)* normalize $\widehat{\mathbf{w}}$ by a constant ϵ so that all the individual power constraints are satisfied. In its first step, this algorithm tries to find the set of users that, when replacing the individual power constraints with a total power constraint, can provide the (approximately) best averaged receive SNR.

Table III demonstrates the maximum, the minimum and the averaged ratios achieved for running the algorithms on 100 independent random generations of the channel. Note that the approximation ratio for a solution $\mathbf{w}^*$ is calculated by $\alpha = \frac{v_1^{\mathrm{CP}}(\mathbf{w}^*)}{v_1^{\mathrm{SDP}}(\mathbf{X}^*)}$.

TABLE III
APPROXIMATION RATIO OF THE PROPOSED AND SPCA ALGORITHMS

	Al. 1 Min	**Al. 1 Mean**	**Al. 1 Max**	**S-PCA Min**	**S-PCA Mean**	**S-PCA Max**
N=10, $Q = \frac{M}{4}$	1.29	1.49	1.79	1.78	2.57	5.22
N=20, $Q = \frac{M}{4}$	1.30	1.40	1.54	1.57	2.43	4.36
N=30, $Q = \frac{M}{4}$	1.22	1.35	1.62	1.70	2.39	3.51
N=10, $Q = \frac{M}{3}$	1.20	1.35	1.52	1.75	2.59	3.58
N=20, $Q = \frac{M}{3}$	1.18	1.30	1.47	1.51	2.49	4.06
N=30, $Q = \frac{M}{3}$	1.16	1.28	1.45	1.57	2.46	4.05

In Fig. 3 we plot the performance of the algorithms for different sizes of the network. For a given network size, we choose Q to be $\frac{M}{5}$ and let $N = M$. For each network (Q, M) pair, the algorithm is run for 100 independent realizations of the channel covariance matrices. We again plot the maximum, the minimum and the averaged approximation ratios achieved among those 100 realizations. In Fig. 4, similar experiment is conducted with fixed number of group size $Q = 10$ for all network sizes.



Fig. 3. Approximation ratio for admission control with different network sizes. $M \in [10, 20, 30, 40, 50, 60, 70]$, $Q = (\frac{M}{5})$, $P_{\text{tot}} = 10dB$, $N = M$, 100 independent realizations of channel.



Fig. 4. Approximation ratio for admission control with different network sizes. $M \in [20, 30, 40, 50, 60, 70]$, $Q = 10$, $P_{\text{tot}} = 10$dB, $N = M$, 100 independent realizations of channel.

In Table IV, we demonstrate the performance of the proposed algorithm for the max-min scheduling problem (abbreviated as Al. 2). Our algorithm is compared with the following two heuristic benchmark algorithms: 1) randomly partition the users into two groups of size Q and $M-Q$, and for each group solve a PCA problem followed by a normalization step (abbreviated as R-PCA); 2) randomly partition the users into two groups of size Q and $M-Q$, and obtain a solution $\mathbf{w}_1^*$ and $\mathbf{w}_2^*$ following steps S4)–S8) in Table II (abbreviated as R-SDR).

From the above results, it is clear that both of the proposed algorithms deliver high quality solutions (in terms of both the averaged and the worse case performance) to the joint admission control and beamforming problem.

TABLE IV
APPROXIMATION RATIO OF THE ALGORITHM FOR SCHEDULING

	Al. 2 Mean	**Al. 2 Max**	**R-PCA Mean**	**R-PCA Max**	**R-SDR Mean**	**R-SDR Max**
N=10, $Q = \frac{M}{4}$	1.22	1.99	4.54	10.06	2.14	4.25
N=30, $Q = \frac{M}{4}$	1.32	2.03	4.15	7.08	1.89	3.19
N=10, $Q = \frac{M}{3}$	1.55	2.06	5.07	9.89	2.37	4.32
N=30, $Q = \frac{M}{3}$	1.36	2.09	4.29	9.75	2.09	3.35

B. *Grouping for Relay Selection in Relay Networks*

In this section, we demonstrate the performance of our algorithm for the joint relay selection and virtual beamforming problem (abbreviated as Al. 3).

For the relay network, the channel covariances are generated as follows [11], [12]. Assume f_i can be written by $f_i = \hat{f}_i + \tilde{f}_i$, where $\hat{f}_i$ is the mean of f_i and $\tilde{f}_i$ is a zero-mean random variable. Assume that $\tilde{f}_i$, $\tilde{f}_j$ are independent for $i \neq j$, and choose $\hat{f}_i = e^{j\theta_i}/\sqrt{\eta_{f_i}}$ and $\mathrm{var}(\tilde{f}) = \eta_{f_i}/(1+\eta_{f_i})$. In this notation, θ_i is a uniform random variable on the interval $[0,\ 2\pi]$, and η_{f_i} is a parameter that determines the level of uncertainty in the channel coefficient f_i. Similarly, let $g_i = \hat{g}_i + \tilde{g}_i$, with $\hat{g}_i$ and $\tilde{g}_i$ defined similarly as $\hat{f}_i$ and $\tilde{f}_i$. For intuition behind this channel model, we refer the readers to [11], [12]. In our simulation below, $\{\eta_{f_i}\}$ and $\{\eta_{g_i}\}$ are generated randomly from -10 dB to 10 dB, accounting for different uncertainty levels for different users.



Fig. 5. Approximation ratio with different network sizes. $M \in [10, 20, 30, 40, 50, 60]$, $Q = (\frac{M}{2})$, $P_{\mathrm{tot}} = 10\mathrm{dBW}$, 100 independent realizations of channel.



Fig. 6. Averaged received SNR for different algorithms. $M \in [10, 20, 30, 40, 50, 60]$, $Q = (\frac{M}{2})$, $P_{\mathrm{tot}} = 10\mathrm{dBW}$, 100 independent realizations of channel.

Our algorithm is compared against the following three algorithms:

- *Random-GED*: This is a variant of the generalized eigenvalue decomposition (GED) based algorithm proposed in [11, Section IV-B]. In its original form, all the relays are utilized, and the algorithm computes an approximated solution of the max-SNR problem by performing a PCA for the matrix $\mathbf{S}^{-1}\mathbf{F}$, followed by a normalization step to ensure the individual power constraints. To incorporate the selection of relays, we first *randomly* select Q out of M relays, and then perform the PCA and normalization steps.
- *Random-SDR*: In this algorithm, we first *randomly* select Q out of M relays in the network, and then perform the two-step SDR algorithm similarly as the one proposed in Section V (with fixed user-grouping).
- *Greedy algorithm*: This algorithm largely follows from the one proposed in [22], in which users are successively and greedily added to the cooperation set as long as by doing so can improve the received SNR level. As the original algorithm *does not* impose hard cardinality constraint, we slightly modify it by keep adding the users utile the required group size Q is reached. Note that this algorithm requires the knowledge of *perfect* channel states.

In Fig. 5–6, the approximation ratio and the achieved receive SNR of different algorithms is plotted against the size of the network. In Fig. 7–8, similar performance metrics are shown when we increase the relays' transmission powers. In both of these two figures we set $P_0 = 0$ dBW and $Q = \frac{M}{2}$. We see that the proposed algorithm is close to the optimal solution across all values of individual power constraints and for all network sizes simulated, while the other three algorithms perform relatively worse in all the experiments. Furthermore, the proposed algorithm has significantly better “worse case” performance than the random-SDR algorithm (see Fig. 5 and Fig. 7).



Fig. 7. Approximation ratio for different algorithms. $M = 30$, $Q = (\frac{M}{2})$, $P_{\rm tot} = [0, 5, 10, 15, 20, 25, 30, 35, 40]$ dBW, 100 independent realizations of channel.



Fig. 8. Averaged receive SNR for different algorithms. $M = 30$, $Q = (\frac{M}{2})$, $P_{\rm tot} = [0, 5, 10, 15, 20, 25, 30, 35, 40]$ dBW, 100 independent realizations of channel.

VII. DISCUSSION AND CONCLUDING REMARKS

This paper addresses the important problem arises in the virtual multi-antenna systems, namely the joint user grouping and the virtual beamformer design problem. In the aim of designing practical algorithms with provable theoretical performance, we focus on simple (yet important) scenarios in which either multiple transmitters cooperatively transmit to a receiver, or a single transmitter transmits to the receiver with the help of a set of cooperative relays.

For different application scenarios, the problems are formulated as cardinality constrained programs, and efficient algorithms based on semi-definite relaxation are proposed. The quality of the solutions is evaluated both theoretically and via numerical simulation. Furthermore, we have established the complexity status for various problems studied in this work, which we summarize below in Table V.

TABLE V
SUMMARY OF COMPLEXITY RESULTS

	Admission Control			**Scheduling (2-Slot)**		
	General	**Diagonal**	**Rank 1**	**General**	**Diagonal**	**Rank 1**
VMIMO	NP-Hard	Ploy. Time Solvable	Ploy. Time Solvable	NP-Hard	NP-Hard	NP-Hard
VMIMO-Relay	NP-Hard	Ploy. Time Solvable	Unknown	NP-Hard	NP-Hard	Unknown

The proposed approach to virtual beamforming can be extended in many interesting directions. Theoretically, it is desirable to develop approximation bounds for the relay selection problem as well as to further sharpen the bounds for the scheduling problem so that it is independent of the problem data (that is, independent of the channel covariance matrices).

Practically, we expect that our approach can be applied and extended to many other interesting scenarios, even beyond the virtual multi-antenna systems. For example, in the user selection problem, to mitigate the interference to a neighboring co-existing system, one could further impose a *total interference* constraint of the form $\mathbb{E}[|\mathbf{w}^H\mathbf{g}|^2] \le I$ to the selected group of users, where g represents the channel between the users and the BS of the neighboring system (e.g., see [32] for an application of this model in the cognitive ratio network). By using the similar algorithm as proposed in Section III, it is possible to show that the obtained solution achieves an approximation ratio of $\alpha_4 = \frac{8M\lambda_1(\mathbf{R})\lambda_1(\mathbf{G})}{Q\lambda_M(\mathbf{R})\lambda_M(\mathbf{G})}\ln(5(Q+1))$ with $\mathbf{G} \triangleq \mathbb{E}[\mathbf{g}\mathbf{g}^H]$. Another interesting direction will be to extend the proposed algorithm to uplink networks with multiple groups of users interfering with each other, or to relay networks with multiple pairs of transceivers (similarly as those discussed in [12]). Additionally, the proposed approach may prove to be useful in designing future multi-cell cellular systems, where not all, but a subset of BSs can jointly transmit and receive signals for a given mobile user (see recent work [20], [21], [35] on the so-called partial ComP technique).

REFERENCES

[1] G.J. Foschini, K. Karakayali, and R.A. Valenzuela, “Coordinating multiple antenna cellular networks to achieve enormous spectral efficiency,” *IEE Proceedings Communications*, vol. 153, no. 4, pp. 548 – 555, august 2006.

[2] D. Gesbert, S. Hanly, H. Huang, S. Shamai, O. Simeone, and W. Yu, “Multi-cell MIMO cooperative networks: A new look at interference,” *IEEE Journal on Selected Areas in Communications*, vol. 28, no. 9, pp. 1380 –1408, december 2010.

[3] R. Irmer, H. Droste, P. Marsch, M. Grieger, G. Fettweis, S. Brueck, H.-P. Mayer, L. Thiele, and V. Jungnickel, “Coordinated multipoint: Concepts, performance, and field trial results,” *IEEE Communications Magazine*, , no. 2, pp. 102–111, 2011.

[4] G. Caire and S. Shamai, “On the achievable throughput of a multiantenna Gaussian broadcast channel,” *IEEE Transactions on Information Theory*, vol. 49, no. 7, pp. 1691 – 1706, july 2003.

[5] W. Yu and T. Lan, “Transmitter optimization for the multi-antenna downlink with per-antenna power constraints,” *IEEE Transactions on Signal Processing*, vol. 55, no. 6, pp. 2646 –2660, june 2007.

[6] Q. H. Spencer, A. L. Swindlehurst, and M. Haardt, “Zero-forcing methods for downlink spatial multiplexing in multiuser mimo channels,” *IEEE Transactions on Signal Processing*, vol. 52, no. 2, pp. 461 – 471, feb. 2004.

[7] J. Zhang, R. Chen, J.G. Andrews, A. Ghosh, and R.W. Heath, “Networked MIMO with clustered linear precoding,” *IEEE Transactions on Wireless Communications*, , no. 8, pp. 1910–1921, 2009.

[8] R. Zhang, “Cooperative multi-cell block diagonalization with per-base-station power constraints,” *IEEE Journal on Selected Areas in Communications*, vol. 28, no. 9, pp. 1435 –1445, december 2010.

[9] J.N. Laneman and G.W. Wornell, “Distributed space-time-coded protocols for exploiting cooperative diversity in wireless networks,” *IEEE Transactions on Information Theory*, vol. 49, no. 10, pp. 2415 – 2425, oct. 2003.

[10] A. Sendonaris, E. Erkip, and B. Aazhang, “User cooperation diversity. part i. system description,” *IEEE Transactions on Communications*, vol. 51, no. 11, pp. 1927 – 1938, nov. 2003.

[11] V. Havary-Nassab, S. Shahbazpanahi, A. Grami, and Z.-Q. Luo, “Distributed beamforming for relay networks based on second-order statistics of the channel state information,” *IEEE Transactions on Signal Processing*, vol. 56, no. 9, pp. 4306 –4316, sept. 2008.

[12] S. Fazeli-Dehkordy, S. Shahbazpanahi, and S. Gazor, “Multiple peer-to-peer communications using a network of relays,” *IEEE Transactions on Signal Processing*, vol. 57, no. 8, pp. 3053 –3062, aug. 2009.

[13] S. Nam, M. Vu, and V. Tarokh, “Relay selection methods for wireless cooperative communications,” in *CISS 2008.*, march 2008, pp. 859 –864.

[14] Y. Zhao, R. Adve, and T. Lim, “Improving amplify-and-forward relay networks: Optimal power allocation versus selection,” in *2006 IEEE International Symposium on Information Theory*, july 2006, pp. 1234 –1238.

[15] A. S. Ibrahim, A. K. Sadek, W. Su, and K. J. Ray Liu, “Cooperative communications with relay-selection: When to cooperate and whom to cooperate with?,” *IEEE Transactions on Wireless Communications*, vol. 7, pp. 2814–2827, 2008.

[16] Y. Jing and H. Jafarkhani, “Network beamforming using relays with perfect channel information,” *IEEE Trans. Inf. Theor.*, vol. 55, no. 6, pp. 2499–2517, June 2009.

[17] D. J. Love, R. W. Heath, V. K. N. Lau, D. Gesbert, B.D. Rao, and M. Andrews, “An overview of limited feedback in wireless communication systems,” *IEEE JSAC*, vol. 26, no. 8, pp. 1341 –1365, 2008.

[18] C. T. K. Ng and H. Huang, “Linear precoding in cooperative MIMO cellular networks with limited coordination clusters,” *IEEE Journal on Selected Areas in Communications*, vol. 28, no. 9, pp. 1446 –1454, december 2010.

[19] A. Papadogiannis and G.C. Alexandropoulos, “The value of dynamic clustering of base stations for future wireless networks,” in *2010 IEEE International Conference on Fuzzy Systems (FUZZ)*, july 2010, pp. 1 –6.

[20] M. Hong, R. Sun, and Z.-Q. Luo, “Joint base station clustering and beamformer design for partial coordinated transmission in heterogenous networks,” 2012, under revision.

[21] S.-J. Kim, S. Jainand, and G.B. Giannakis, “Backhaul-constrained multi-cell cooperation using compressive sensing and spectral clustering,” in *2012 IEEE SPWAC*, July 2012.

[22] Y. Jing and H. Jafarkhani, “Single and multiple relay selection schemes and their achievable diversity orders,” *IEEE Transactions on Wireless Communications*, vol. 8, no. 3, pp. 1414 –1423, march 2009.

[23] C.-H. Yu and O. Tirkkonen, “Opportunistic multiple relay selection with diverse mean channel gains,” *IEEE Transactions on Wireless Communications*, vol. 11, no. 3, pp. 885 –891, march 2012.

[24] D.S. Michalopoulos, G.K. Karagiannidis, T.A. Tsiftsis, and R.K. Mallild, “Wlc41-1: An optimized user selection method for cooperative diversity systems,” in *IEEE GLOBECOM ’06.*, 27 2006-dec. 1 2006, pp. 1 –6.

[25] M. R. Garey and D. S. Johnson, *Computers and Intractability: A guide to the Theory of NP-completeness*, W. H. Freeman and Company, San Francisco, U.S.A, 1979.

[26] Z.-Q. Luo, W.-K. Ma, A.M.-C. So, Y. Ye, and S. Zhang, “Semidefinite relaxation of quadratic optimization problems,” *IEEE Signal Processing Magazine*, vol. 27, no. 3, pp. 20 –34, may 2010.

[27] Z.-Q. Luo, N. D. Sidiropoulos, P. Tseng, and S. Zhang, “Approximation bounds for quadratic optimization with homogeneous quadratic constraints,” *SIAM Journal on Optimization*, pp. 1–28, 2007.

[28] B. Moghaddam, Y. Weiss, and S. Avidan, “Generalized spectral bounds for sparse LDA,” in *Proceedings of the 23rd international conference on Machine learning*, New York, NY, USA, 2006, ICML ’06, pp. 641–648, ACM.

[29] Baback Moghaddam, Yair Weiss, and Shai Avidan, “Spectral bounds for sparse pca: Exact and greedy algorithms,” in *NIPS’05*, 2005.

[30] M. X. Goemans and D. P. Williamson, “Improved approximation algorithms for maximum cut and satisfiability problems using semidefinite programming,” *Journal of ACM*, vol. 42, no. 6, pp. 1115–1145, Nov. 1995.

[31] A. Nemirovski, C. Roos, and T. Terlaky, “On maximization of quadratic form over intersection of ellipsoids with common center,” *Mathematical Programming*, vol. 86, no. 3, pp. 463–473, 1999.

[32] Y. J. Zhang and A. M.-C. So, “Optimal spectrum sharing in mimo cognitive radio networks via semidefinite programming,” *IEEE Journal on Selected Areas in Communications*, pp. 362–373, 2011.

[33] A. W. Marshall, I. Olkin, and B. C. Arnold, *Inequalities: Theory of Majorization And Its Applications*, Springer, 2010.

[34] C. J. Green, “Large deviation results for combinatorics and number theory,” available at: www.dpmms.cam.ac.uk/ bjg23/papers/deviate.pdf.

[35] P. Marsch and G. Fettweis, “Static clustering for cooperative multi-point (comp) in mobile communications,” in *2011 IEEE International Conference on Communications (ICC)*, june 2011, pp. 1 –6.